

IP Surveillance Solutions

Ideal for home, office and professional use, These high-quality security solutions will protect the things that matter most



Public Surveillance



Transportation Surveillance



Harsh Environment Surveillance

www.level1.com | one world_one brand_one level_



Contents

Introduction	2-3
Camera	4-16
- Business	4-13
Fixed Camera	
Zoom Camera	
Fixed Dome Camera	
Panoramic Dome Camera	
PTZ Dome Camera	
- Home/Small Office	13-16
Fixed Camera	
PT Camera	
Lens & Outdoor Enclosure	17
Optional Accessories	18-19
OneSecure Video Management Software	20-22
Network Video Recorder (NVR)	23-24
Hybrid Interoperable	25-26
Installation	27-33
Installation over PoE Network by PoE Switch	
PoE Extender over Hybrid Fiber	
Installation over PoE Network by PoE Repeater	
Simple yet durable, no software required	
Installation over PoE Network by PoE Injector and PoE Splitter	
Installation over PoE Network by PoE Injector Hubs	
Installation over Wireless Network	
Application Instauration	34-35
Installation over 2-Wire	
Surveillance Deployment for Transportation	
Index	36

IP network cameras – a growing market

According to a study by the Academia.edu group, the worldwide video surveillance market is destined to increase in volume by nearly 25% between 2013 and 2018. Forecasts suggest that a steady rate of growth will continue into the foreseeable future, with a clear trend developing among system integrators who are moving away from analog systems to take advantage of the many benefits offered by new IP surveillance networks.



Why LevelOne for IP Surveillance?

LevelOne has a long-standing history as a leading vendor of innovative network solutions. We've taken the same progressive approach to the emerging digital surveillance market.

The LevelOne "total surveillance solution" includes a wide selection of network cameras, a comprehensive range of professional surveillance-management software packages, and an equally wide choice of quality Network Video Recorders (NVR) and Network Attached Storage (NAS) devices. We also provide all the necessary networking components like switches, PoE devices and accessories, which allow users to build an advanced surveillance network with guaranteed compatibility and technical support.

If you are searching for a high-quality surveillance monitoring solution, LevelOne offers a comprehensive range of networking products to satisfy all your technological needs.





Future-Proof Security Technology from LevelOne

Security cameras have become omnipresent in many countries. LevelOne's advanced IP surveillance systems provide a single environment that combines intelligent video analytics, universal IP connectivity to network cameras, access control devices and burglar alarm systems for day and night use. LevelOne helps users to attain a higher level of security than ever before - with less cost and less effort – making the home, the workplace and the streets safer for everyone.



Uncompromising Image Quality

Pure digital image, no image degradation. For instance, one 1.3 Megapixel camera can replace up to six analog cameras in many applications, like banks and petrol stations, and still produce a better recording of faces and registration plates.



An IP based camera only needs to use one

Cat.5 cable, whereas an analogue camera uses

Coaxial cable to transfer video, an RS-485 cable

to transfer the control signal and another cable

for IO In/Out. IP cameras massively reduce the

cost of installation, and the remote system access

reduces the cost of maintenance and problem

Simple Connectivity

solving.



Distributing

Take snapshots of an intruder or an incident and send by e-mail to the police, or the appropriate authorities. In addition to this, images can be monitored from one central source, offering great efficiency and huge cost savings. Mobile monitoring is also widely available using the OneSecure software provided with each LevelOne camera.



Future Proof

IP surveillance is completely scalable, allowing expansion at an incremental cost when required. By integrating it fully with existing network infrastructure over single or multiple sites, users can ensure their investment is protected.



Remote Access/Live View

Able to broadcast live images to your handheld mobile phone or tablet and supports 3GPP/RSTP format via a 3G or 4G mobile phone.



Free Bundled Professional Software

All LevelOne network cameras come with free bundled software, providing a large range of comprehensive features. Users are able to monitor up to 64 channels simultaneously over the Internet.

The LevelOne Business IP network camera series

Whereas outdoor surveillance previously only appeared in banks or high-security areas, there is a growing realisation that high levels of surveillance in public areas can help deter crime and antisocial behaviour. In order to help protect communities from dangerous elements, LevelOne has developed an Enterprise level of network cameras.

For outdoor camera network deployments, our products feature IP65 and higher-rated waterproof housing accessories to protect against even the most severe weather.

Applications

City Surveillance

LevelOne Advance Speed Dome Camera, which includes WDS(Wide Dynamic Range) for high contrast environments, infrared Illuminators for night viewing, motion detection and 360° continuous pan - all designed to build a safer city.



Transportation

LevelOne Fixed Camera and Fixed Dome Camera, providing live viewing and recording in crystal clear images. Provides effective, convenient monitoring of information – anywhere, at any time.



Retail Store & Coffee Shop

LevelOne offers a cost-effective, easy installation indoor P/T/Z camera, featuring flexible 355°pan, 135°tilt and 4x digital zoom functionality. The ideal solution for use in retail, coffee shops, hotel lobbies and warehouses, providing a secure environment for customers and staff.





Fixed Camera

The viewing direction of a fixed network camera usually offers a single, static viewing area once the camera is mounted. However, LevelOne fixed network cameras have several optional, exchangeable C/S mount types of lenses and outdoor housing, giving users the flexibility of changing the hardware to suit a number of diverse monitoring environments.

	Fixed Camera				
Models	FCS-1131	FCS-1152	FCS-5051		
Product Image	Onvif		Onvif		
	Renative		Ô		
Name	Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night	Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR	Fixed Network Camera, IR LEDs, PoE 802.3af, IR LEDs, 2-Megapixel, Day & Night, Outdoor		
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps		
Wireless	-				
Power Input	DC12V / 802.3af PoE	802.3af PoE	DC12V / AC24V / 802.3af PoE		
Compression	H.264 / MJPEG	H.264 Hihg Profile / MJPEG	H.264 / MJPEG		
Max. Resolution & Frame	1920x1080, 15 fps at 1920x1080;	2592x1944, 15 fps at 2592 x 1944;	1920x1080, 15 fps at 1920x1080;		
Rate	30 fps at 1280x1024	15 fps at 2048x1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	30 fps at 1280x1024		
Horizontal View Angle	65.4°	70.9° - 29.2°	87.6°		
Sensor	2-Megapixel 1/2.7" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	2-Megapixel 1/2.7" Progressive Scan CMOS		
Lens	C/CS-mount, Fixed-focal, f=4.0mm, F1.5	Vari-focal, DC iris, Manual focus, f2.8-12mm, F1.4	Board lens, Fixed-focal, f=3.6mm, F1.5		
Minimum Illumination	Color: 0.2 lux at F1.5 B/W: 0.02 lux at F1.5	Color: 0.1 lux at F1.4 B/W: 0.05 lux at F1.4"	Color: 0.2 lux at F1.5 B/W: 0.02 lux at F1.5		
shutter (sec)	1~ 1/10,000	1/5 ~ 1/10,000	1~ 1/10,000		
IRLED /Type/ Distance	-	-	V (25m)		
ICR (IR-Cut Filter Removal)	V	V	V		
AGC/AWB/AES	V	V	V		
Wide Dynamic Range	Basic WDR (74 dB)	Basic WDR (74 dB)	Basic WDR (74 dB)		
Digital Noise Reduction	3DNR	2DNR	3DNR		
Privacy Mask	V	-	V		
DDNS Support	V	V	V		
Operation Temperature	-10°C ~ 50°C	-10°C ~ 50°C	-10°C ~ 50°C		
Approvals	CE, FCC	CE, FCC	CE, FCC		
Audio Codec	G.711 / G.726 2-way (Line-in, Line-out)	G.711	G.711/G.726		
Audio P/T/Z	2-way (Line-in, Line-out) - / - / Digital: 8x	- Digital Zoom to very high detail available on	2-way (Line-in, Line-out) - / - / Digital:8x		
		Software	5		
Local storage	MicroSDHC card slot	MicroSDHC/ MicroSDXC card slot	Micro SD/SDHC card slot		
6.11 DL	(card not included)	(card not included)	(card not included)		
Cell Phone Web Browswer	3GPP / RTSP	RTSP	3GPP / RTSP		
	IE/Safari (Mac/iOS) ¹ /Firefox ¹	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE/Safari (Mac/iOS) ¹ /Firefox ¹		
Optional Accessories	Outdoor Housing: BOH-1400 / BOH-1401 BOH-1410 / BOH-1411 Lens: CAS-1400	Bracket: CAS-3104	-		
Digital I/O	1DI/ 1DO	1DI/ 1DO	1DI/ 1DO		

V=Yes -=No 1. View your camera by http://camera_IP_Add:8008

2. View your camera by http://camera_IP_Add/img/mjpeg.htm 3. Java and QuickTime is required

	Fixed Camera					
Models	FCS-5053	FCS-5054	FCS-5056			
Product Image		Onvir				
Name	Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs	Fixed Network Camera, 3-Megapixel, PoE 802.3af, Outdoor, Day & Night, IR LEDs, WDR	Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR			
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps			
Wireless	-	-	-			
Power Input	802.3af PoE	802.3af PoE	802.3af PoE			
Compression	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG			
Max. Resolution & Frame	2048 x 1536,	2048 x 1536,	2048 x 1536,			
Rate	15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	20 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240			
Horizontal View Angle	62.7°	70.5°-28.8°	50.2° ~ 4.69°			
Sensor	3-Megapixel 1/3.2" Progressive Scan CMOS	3-Megapixel 1/3" Progressive Scan CMOS	3-Megapixel 1/3.2" Progressive Scan CMOS			
Lens	Fixed focal, Fixed iris, Fixed focus, f4.2mm, F1.8	Vari-focal, Fixed iris, Manual focus, f2.8-12mm, F1.4	Fixed focal, Fixed iris, Fixed focus, f4.2mm, F1.8			
Minimum Illumination	Color: 0.1 lux at F1.8 B/W: 0 lux (IR LED on)	Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on)	Color: 0.1 lux at F1.8 B/W: 0 lux (IR LED on)			
shutter (sec)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000			
RLED /Type/ Distance	V (20m)	V (30m)	V (30m)			
CR (IR-Cut Filter Removal)	V	V	V			
AGC/AWB/AES	V	V	V			
Wide Dynamic Range	-	Superior WDR (110 dB)	Basic WDR (74 dB)			
Digital Noise Reduction	2DNR	2DNR	2DNR			
Privacy Mask	-	-	-			
DDNS Support	V	V	V			
Operation Temperature	-40°C ~ 50°C	-40°C ~ 50°C	-40°C ~ 50°C			
Approvals	CE, FCC, IP66	CE, FCC, IP67, IK10	CE, FCC, IP68, IK10, NEMA 4X			
Audio Codec	G.711	G.711	G.711			
Audio	-	2-way (Line-in, Line-out)	-			
P/T/Z	Digital Zoom to very high detail available on Software	Digital Zoom to very high detail available on Software	Digital Zoom to very high detail available on Softwar			
Local storage	-	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)			
Cell Phone	RTSP	RTSP	RTSP			
Web Browswer	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime			
Optional Accessories	Wall Mount kit: CAS-3103	Pole Mount kit: CAS-2504	Wall Mount kit: CAS-3103			
Digital I/O		1DI/ 1DO				

V=Yes -=No

1. View your camera by http://camera_IP_Add:8008 2. View your camera by http://camera_IP_Add/img/mjpeg.htm 3. Java and QuickTime is required

Fixed Camera				
FCS-5057	FCS-5064	FCS-5061	FCS-5063	
	Onvie	Onvir		
Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR 10/100Mbps	Fixed Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR 10/100Mbps	Fixed Network Camera, IR LEDs, PoE+ 802.3af/at, 5-Megapixel, Day & Night, Outdoor 10/100Mbps	Fixed Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR 10/100Mbps	
- 802.3af PoE	- 802.3af PoE	- AC24V / 802.3at PoE Plus	- 802.3af PoE	
H.264 High Profile, MJPEG 2048x1536, 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	H.264 High Profile, MJPEG 2592x1944, 15 fps at 2592 x 1944; 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480 ; 15 fps 320 x 240 ; 15 fps at 320 x 240	H.264/ MPEG4 2592x1944, 10 fps at 2592x1944; 15 fps at 2048x1536; 30 fps at 1920x1080	H.264 High Profile, MJPEG 2592x1944, 15 fpsat 2592 x 1944; 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	
70.5° ~ 28.2°	69.2° ~ 28.2°	90°	62.7°	
3-Megapixel 1/3.2" Progressive Scan CMOS Vari-focal, Fixed iris, Manual focus, f2.8-12mm, F1.4 Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on) 1/5 ~ 1/10,000	5-Megapixel 1/3.2" Progressive Scan CMOS Vari-focal, Fixed iris, Manual focus, f2.8-12mm, F1.4 Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on) 1/5 ~ 1/10,000	5-Megapixel 1/2.5" Progressive Scan CMOS Board lens, fixed-focal, f=4.0 mm, F1.6 Color: 0.1 lux at F1.6 B/W: 0 lux at F1.6 1~1/10,000	5-Megapixel 1/3.2" Progressive Scan CMOS Fixed focal, Fixed iris, Fixed focus, f4.2mm, F1.8 Color: 0.1 lux at F1.8 B/W: 0 lux (IR LED on) 1/5 ~ 1/10,000	
V (30m) V V	V (30m) V V	V (25m) V V	V (30m) V V	
Basic WDR (74 dB) 2DNR -	Basic WDR (74 dB) 2DNR	Basic WDR (74 dB) 3DNR V	Basic WDR (74 dB) 2DNR -	
V -40°C ~ 50°C	V -40°C ~ 50°C	V -40°C ~ 50°C (AC 24V / PoE-Plus)	V -40°C ~ 50°C	
CE, FCC, IP68, IK10, NEMA 4X	CE, FCC, IP68, IK10, NEMA 4X	CE, FCC	CE, FCC, IP68, IK10, NEMA 4X	
G.711 2-way (Line-in, Line-out)	G.711 2-way (Line-in, Line-out)	G.711 / G.726 2-way (Line-in, Line-out)	G.711	
Digital Zoom to very high detail available on Software MicroSDHC/MicroSDXC card slot (card not included)	Digital Zoom to very high detail available on Software MicroSDHC/MicroSDXC card slot (card not included) RTSP	- / - / Digital: 8x Micro SD/SDHC card slot (card not included)	Digital Zoom to very high detail available on Software MicroSDHC/MicroSDXC card slot (card not included) RTSP	
RTSP IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime Wall Mount kit: CAS-3103	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime Wall Mount kit: CAS-3103	3GPP / RTSP IE/Safari (Mac/iOS) ¹ /Firefox ¹	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime Wall Mount kit: CAS-3103	
1DI/ 1DO	1DI/ 1DO	1DI/ 1DO	-	

Zoom Camera

The zoom cameras feature optical zoom, enabling a closer view of the subject before taking the images. With 2/3DNR (2/3-Dimension Noise Reduction) and WDR (Wide Dynamic Range), this range produces highly reliable, crystal-clear images under any conditions. The perfect solution for day/night surveillance installations such as school campuses, railway stations and parking lots.

	Zoom Camera				
Models	FCS-1150	FCS-1160	FCS-5042	FCS-5055	FCS-5065
Product Image	Οηνιγ	Οηνιγ	Οηνιγ		
	0]	0]		0.1	
Name	Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR	Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR	Zoom Network camera, PoE 802.3af, IR LEDs, 2-Megapixel, Day & Night, Outdoor, 10x	Zoom Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, 12x, WDR	Zoom Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, 12x, WDR
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps	10/100Mbps	10/100Mbps
Wireless	-	-	-	-	-
Power Input	DC12V / 802.3af PoE	DC12V / 802.3af PoE	DC12V 1.5A / 802.3af PoE	DC 12V / 802.3af PoE	DC 12V / 802.3af PoE
Compression	H.264 Hihg Profile / MJPEG	H.264 Hihg Profile / MJPEG	H.264 / MPEG4 / MJPEG	H.264 Hihg Profile / MJPEG	H.264 Hihg Profile / MJPEG
Max. Resolution & Frame	2048 x 1536,	2592 x 1944,	1920 x 1080,	2048 x 1536,	2592 x 1944,
Rate	20 fps at 2048 x 1536;	15 fps at 2592 x 1944;	25 fps at 1920 x 1080	20 fps at 2048 x 1536;	15 fps at 2592 x 1944;
	30 fps at 1920 x 1080;	15 fps at 2048 x 1536;		30 fps at 1920 x 1080;	15 fps at 2048 x 1536;
	30 fps at 1280 x 720;	30 fps at 1920 x 1080; 30 fps at 1280 x 720;		30 fps at 1280 x 720;	30 fps at 1920 x 1080;
	30 fps at 640 x 480; 15 fps at 320 x 240	30 fps at 640 x 480;		30 fps at 640 x 480; 15 fps at 320 x 240	30 fps at 1280 x 720; 30 fps at 640 x 480;
	13 Ips at 320 x 240	15 fps at 320 x 240		13 ips at 320 x 240	15 fps at 320x240
Horizontal View Angle	50.2°-4.69°	48.4°-4.8°	Fov(D), 66.6° ~ 7.2°	50.2° ~ 4.69°	48.4° ~ 4.8°
Sensor	3-Megapixel 1/3" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	2-Megapixel 1/2.7" Progressive Scan CMOS	3-Megapixel 1/3" Progressive Scan CMOS	5-Megapixel 1/3" Progressive Scan CMOS
Lens	Zoom, DC iris, Auto focus,	Zoom, DC iris, Auto focus,	Zoom, Auto iris, Auto focus,	Zoom, DC iris, Auto focus,	Zoom, DC iris, Auto focus,
	f5.2-62.4mm, F1.8-3.0	f5.2-62.4mm, F1.8-3.0	f=4.9 ~ 49mm, F1.8 ~3.0	f5.2-62.4mm, F1.8-3.0	f5.2-62.4mm, F1.8-3.0
Minimum Illumination	Color: 0.1 lux	Color: 0.1 lux	Color: 1.0 lux at F2.0	Color: 0.1 lux at F1.8	Color: 0.1 lux at F1.8
- Location (B/W: 0.05 lux at F1.8	B/W: 0.05 lux at F1.8	B/W: 0 lux (IR LED on)	B/W: 0 lux (IR LED on)	B/W: 0 lux (IR LED on)
shutter (sec)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000
IRLED /Type/ Distance ICR (IR-Cut Filter Removal)	- V	- V	V (30m) V	V (40m) V	V (40m)
AGC/AWB/AES	V	V	V	V	V
Wide Dynamic Range	Superior WDR (110 dB)	Basic WDR (74 dB)	Basic WDR (74 dB)	Superior WDR (110 dB)	Basic WDR (74 dB)
Digital Noise Reduction	2DNR	2DNR	3DNR	2DNR	2DNR
Privacy Mask	-	-	-	-	-
DDNS Support	V	V	V	V	V
Operation Temperature	-10°C ~ 50°C	-10°C ~ 50°C	-20°C ~ 50°C	-40°C ~ 50°C	-40°C ~ 50°C
Approvals	CE, FCC	CE, FCC	CE, FCC, IP66	CE, FCC, IP67, IK10, NEMA 4X	CE, FCC, IP67, IK10, NEMA 4X
Audio Codec	G.711	G.711	G.711 / AMR / AAC	G.711	G.711
Audio	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)	2-way (External microphone)	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)
Р/Т/Z	- / - / Optical: 12x	- / - / Optical: 12x	- / - /Optical: 10X, Digital: 4X	- / - / Optical: 12x	- / - / Optical: 12x
Local storage	MicroSDHC/MicroSDXC card	MicroSDHC/MicroSDXC card	MicroSDHC card slot	MicroSDHC/MicroSDXC card	MicroSDHC/MicroSDXC card
	slot (card not included)	slot (card not included)	(card not included)	slot (card not included)	slot (card not included)
Cell Phone	RTSP	RTSP	3GPP/ RTSP	RTSP	RTSP
Web Browswer	IE 8, IE 9, IE 10, IE 11, Firefox	IE 8, IE 9, IE 10, IE 11, Firefox	IE 6.x or above/Firefox/	IE 8, IE 9, IE 10, IE 11, Firefox	IE 8, IE 9, IE 10, IE 11, Firefox
	with VLC, Chrome with VLC,	with VLC, Chrome with VLC,	Chrome/Safari	with VLC, Chrome with VLC,	with VLC, Chrome with VLC,
0	Safari with Quicktime	Safari with Quicktime		Safari with Quicktime	Safari with Quicktime
Optional Accessories	Bracket: CAS-3105	Bracket: CAS-3105	-	Pole Mount kit: CAS-2504. Ceiling Bracket: CAS-3300	Pole Mount kit: CAS-2504. Ceiling Bracket: CAS-3300
Digital I/O	1DI / 1DO	1DI / 1DO	-	1DI / 1DO	1DI / 1DO

V=Yes -=No

1. View your camera by http://camera_IP_Add:8008 2. View your camera by http://camera_IP_Add/img/mjpeg.htm

3. Java and QuickTime is required



Fixed Dome Camera

Compared to an ordinary network camera, fixed dome cameras are a compact device with dome housing, offering a discreet and unobtrusive design that can be installed on either a ceiling or wall. Furthermore, the design of the camera makes it hard to know which direction the camera is pointing, so it acts as an effective deterrent over a wide area. All LevelOne fixed dome cameras comply with IEEE 802.3af PoE standards for easy network deployment.

	Fixed Dome Camera				
Models	FCS-3053	FCS-3054	FCS-3055		
Product Image					
Name	Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs	Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af	Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR		
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps		
Wireless	-	-	-		
Power Input	802.3af PoE	802.3af PoE	802.3af PoE		
Compression	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG		
Max. Resolution & Frame Rate	2048 x 1536, 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	2048 x 1536, 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	2048 x 1536, 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240		
Horizontal View Angle	72°	83.3°	70.5° - 28.2°		
Sensor	3-Megapixel 1/3.2" Progressive Scan CMOS	3-Megapixel 1/3.2" Progressive Scan CMOS	3-Megapixel 1/3.2" Progressive Scan CMOS		
Lens	Fixed focal, Fixed iris, Fixed focus, f3.6mm, F1.8	Fixed focal, Fixed iris, Fixed focus, f2.93mm , F2.0	Vari-focal, Fixed iris, Manual focus, f2.8-12mm, F1.4		
Minimum Illumination	Color: 0.1 lux B/W: 0 lux (IR LED on) at F1.8	0.1 lux at F2.0	Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on)		
shutter (sec)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000		
IRLED /Type/ Distance	V (20m)	-	V (30m)		
ICR (IR-Cut Filter Removal)	V	-	V		
AGC/AWB/AES	V	V	V		
Wide Dynamic Range	-	-	Basic WDR (74 dB)		
Digital Noise Reduction	2DNR	2DNR	2DNR		
Privacy Mask	-	- V	-		
DDNS Support	V	-	V 10%C 50%C		
Operation Temperature Approvals	-10°C ~ 50°	-10°C ~ 50° CE, FCC, IK08	-40°C ~ 50°C CE, FCC, IP67, IK10, NEMA 4X		
Approvais Audio Codec	CE, FCC	G.711	G.711		
Audio Codec	-	-	2-way (Line-in, Line-out)		
P/T/Z	- Digital Zoom to very high detail available on Software	Digital Zoom to very high detail available on Software	Digital Zoom to very high detail available on Software		
Local storage	-	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)		
Cell Phone	RTSP	RTSP	RTSP		
Web Browswer	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime		
Optional Accessories	Mount kit: CAS-2101, Wall Mount kit: CAS-2313, Flush Mount Kit: CAS-3002	-	Mount kit: CAS-2101, Wall Mount kit: CAS-2314, Flush Mount Kit: CAS-3002		
Digital I/O	-	-	1DI / 1DO		

	Fixed Dome Camera					
Madelsage	FCS-3063	FCS-3064	FCS-3065	FCS-3071		
			Οηνιε			
		Concernance of the second				
	A starting			14		
	Ale Ale	6 404.20				
Vame						
	Fixed Dome Network Camera,	Fixed Dome Network Camera,	Fixed Dome Network Camera,	Fixed Dome Network Camera, PoE		
	5-Megapixel, PoE 802.3af, Day & Night,	5-Megapixel, PoE 802.3af, Day &	5-Megapixel, PoE 802.3af, WDR	802.3af, 2-Megapixel		
LAN Connection	IR LEDs, WDR	Night, IR LEDs, WDR				
Wireless	10/100Mbps	10/100Mbps	10/100Mbps	10/100Mbps		
Power Input	-	-	-	-		
Compression	802.3af PoE	802.3af PoE	802.3af PoE	802.3af PoE		
Max. Resolution & Frame	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 / MJPEG		
Rate	2592 x 1944,	2592 x 1944,	2592 x 1944,	1920 x 1080,		
	15 fps at 2592 x 1944;	15 fps at 2592x1944;	15 fps at 2592 x 1944;	15 fps at 1920x1080;		
	15 fps at 2048 x 1536;	15 fps at 2048 x 1536;	15 fps at 2048 x1536;	30 fps at 1280x1024		
	30 fps at 1920 x 1080;	30 fps at 1920 x 1080;	30 fps at 1920 x 1080;			
	30 fps at 1280 x 720;	30 fps at 1280 x 720;	30 fps at 1280 x 720;			
	30 fps at 640 x 480;	30 fps at 640 x 480;	30 fps at 640 x 480;			
	15 fps at 320 x 240	15 fps at 320 x 240	15 fps at 320 x 240			
lorizontal View Angle	72°	66.62° - 28.88°	126.9° (overview area),	78°		
ionzontal view Aligie	12	00.02 - 20.00	77.4° (high detail area)	70		
·		5 Managinal 1/2 2" Dragmaning Case		2-Megapixel 1/2.7" ProgressiveScan		
ensor	5-Megapixel 1/3.2" Progressive Scan	5-Megapixel 1/3.2" Progressive Scan	5-Megapixel 1/3.2" Progressive Scan			
	CMOS Fixed focal, Fixed iris, Fixed focus,	CMOS Vari-focal, Fixed iris, Manual focus,	CMOS Fixed focal, Fixed iris, Fixed focus,	CMOS Board lens, Fixed-focal,		
ens						
	f3.6mm, F1.8	f2.8-12mm, F1.4	f1.9mm, F2.8	f=4.0mm, F1.5		
Minimum Illumination	Color: 0.1 lux at F1.8	Color: 0.1 lux at F1.4	0.1 lux at F2.8	Color: 0.2 lux at F1.5		
	B/W: 0 lux (IR LED on)	B/W: 0 lux (IR LED on)		B/W: 0.02 lux at F1.5		
shutter (sec)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1~ 1/10,000		
RLED /Type/ Distance	V (30m)	V (30m)	-	-		
ICR (IR-Cut Filter Removal)	V	V	-	-		
AGC/AWB/AES	V	V	V	V		
Wide Dynamic Range	Basic WDR (74 dB)	Basic WDR (74 dB)	Basic WDR (74 dB)	-		
Digital Noise Reduction	2DNR	2DNR	2DNR	3DNR		
Privacy Mask	-	-	-	V		
DDNS Support	V	V	V	V		
Operation Temperature	-10°C ~ 50°	-10°C ~ 50°	-10°C ~ 50°	-10°~50°		
Approvals	CE, FCC	CE, FCC, IK09	CE, FCC, IK08	CE, FCC, IP66		
Audio Codec	G.711	G.711	G.711	G.711 / G.726		
Audio		2-way (Line-in, Line-out)	-	-		
P/T/Z	Digital Zoom to very high detail available	Digital Zoom to very high detail	Digital Zoom to very high detail	- / - / Digital: 8x		
	on Software	available on Software	available on Software			
Local storage	-	MicroSDHC/MicroSDXC card slot	MicroSDHC/MicroSDXC card slot	Micro SD/ SDHC card slot		
		(card not included)	(card not included)	(card not included)		
Cell Phone	RTSP	RTSP	RTSP	3GPP/ RTSP		
Web Browswer	IE 8, IE 9, IE 10, IE 11, Firefox with VLC,	IE 8, IE 9, IE 10, IE 11, Firefox with VLC,	IE 8, IE 9, IE 10, IE 11, Firefox with VLC,	IE/Safari (Mac/iOS) ¹ /Firefox ¹		
	Chrome with VLC, Safari with Quicktime	Chrome with VLC, Safari with	Chrome with VLC, Safari with			
		Quicktime	Quicktime			
Optional Accessories	Mount kit: CAS-2101,	Mount kit: CAS-2101,	-	-		
	Wall Mount kit: CAS-2313,	Wall Mount kit: CAS-2313,				
	Flush Mount Kit: CAS-3002	Flush Mount Kit: CAS-3001				
		Hush Mount Nt. CAS-5001				
Digital I/O						
AUTO ALL/UL	· · ·	1DI / 1DO	-	-		

V=Yes -=No

View your camera by http://camera_IP_Add:8008
 View your camera by http://camera_IP_Add/img/mjpeg.htm
 Java and QuickTime is required

Fixed Dome Camera					
FCS-3072	FCS-3081	FCS-3082	FCS-3083	FCS-3101	
		Onvir	Onvir		
Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, WDR, Vandalproof, Vibrationproof 10/100Mbps	Fixed Dome Network Camera, IR LEDs, PoE 802.3af, 2-Megapixel, Day & Night 10/100Mbps	Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR 10/100Mbps	Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR 10/100Mbps	Fixed Dome Network Camera, IR LEDs, PoE 802.3af, 2-Megapixel, Day & Night 10/100Mbps	
802.3af PoE H.264 Hihg Profile / MJPEG 2592 x 1944, 15 fps at 2592x1944; 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 20 fps at 640 x 480;	DC12V / AC24V / 802.3af PoE H.264 / MJPEG 1920 x 1080, 15 fps at 1920x1080; 30 fps at 1280x1024		802.3af PoE H.264 Hihg Profile / MJPEG 2592 x 1944, 15 fps at 2592 x 1944; 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 20 fps at 640 x 480.	DC12V 1.5A / AC24V / 802.3af PoE H.264, MPEG4, MJPEG 1920 x 1080, 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	
30 fps at 640 x 480; 15 fps at 320 x 240 126.9° (overview area), 77.4° (high detail area)	103.5°(W) ~ 34.3°(T)	70.5° - 28.8°	30 fps at 640 x 480; 15 fps at 320 x 240 69.2° - 28.2°	62°	
5-Megapixel 1/3.2" Progressive Scan CMOS Fixed focal, Fixed iris, Fixed focus, f1.9mm, F2.8	2-Megapixel 1/2.7" Progressive Scan CMOS Board lens, Vari-focal, f=3-9mm, F1.2	3-Megapixel 1/3" Progressive Scan CMOS Vari-focal, Fixed iris, Manual focus, f2.8-12mm, F1.4	5-Megapixel 1/3.2" Progressive Scan CMOS Vari-focal, Fixed iris, Manual focus, f2.8-12 mm, F1.4	2-Megapixel 1/2.7" Progressive Scan CMOS Board lens, Fixed-focal, f=4.0mm, F2.0	
Color: 0.1 lux B/W: 0.05 lux at F2.8	Color: 0.2 lux at F1.2 B/W: 0.02 lux at F1.2 1~1/10,000	Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on) 1/5 ~ 1/10,000	Color: 0.1 lux at F1.4 B/W: 0 lux (IR LED on) 1/5 ~ 1/10,000	Color: 0.1 lux at F2.0 B/W: 0 lux (IR LED on) 1/30 ~ 1/1,000,000	
- - V Basic WDR (74 dB)	V (25m) V V Basic WDR (74 dB)	V (30m) V V Superior WDR (110 dB)	V (30m) V V Basic WDR (74 dB)	V (10m) V V Basic WDR (74 dB)	
2DNR 	3DNR V V	2DNR - V	2DNR - V	2DNR - V	
-20°~50° CE, FCC, IP68, IK10, NEMA 4X, EN50155	-10°~50°C (DC 12V/ PoE-Plus) -35°~50°C (AC 24V) CE, FCC, IP66	-40°C ~ 50°C CE, FCC, IP67, IK10, NEMA 4X	-40°C ~ 50°C CE, FCC, IP67, IK10, NEMA 4X	0°C ~40°C CE, FCC	
G.711 1-way (Mic-in) Digital Zoom to very high detail available on Software	G.711 / G.726 2-way (Line-in, Line-out) - / - / Digital: 8x	G.711 2-way (Line-in, Line-out) Digital Zoom to very high detail available on Software	G.711 2-way (Line-in, Line-out) Digital Zoom to very high detail available on Software	AMR / AAC 1-way (Built-in Microphone) -	
MicroSDHC/MicroSDXC card slot (card not included) RTSP	Micro SD/ SDHC card slot (card not included) 3GPP/ RTSP	MicroSDHC/MicroSDXC card slot (card not included) RTSP	MicroSDHC/MicroSDXC card slot (card not included) RTSP	MicroSDHC card slot (card not included) 3GPP/ RTSP	
IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE/Safari (Mac/iOS) ¹ /Firefox ¹	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC,	IE 6.x or above/Firefox/Chrome/Safari	
-	Wall Mount kit: CAS-3101/CAS-3201/CAS-3221 Pole Mount kit: CAS-3261 Ceiling Mount kit: CAS-3100/CAS-3241/CAS-3242 Outdoor Housing: CAS-3000	Mount kit: CAS-2101, Wall Mount kit: CAS-2314, Flush Mount Kit: CAS-3001	Mount kit: CAS-2101, Wall Mount kit: CAS-2314, Flush Mount Kit: CAS-3001	-	
-	1DI / 1DO	1DI / 1DO	1DI / 1DO	-	

Panoramic Dome Camera

The Panoramic Dome Camera allows you to monitor all angles of a location using just one camera. It features a fish-eye lens for a 360° panoramic wide angle view without blind spots. The panoramic coverage ability enables a cost-effective deployment, as fewer cameras need to be installed and maintenance therefore becomes easier and cheaper. It is a perfect solution for stores, schools, offices and lobby applications.

	Panoramic Dome Camera					
Models	FCS-3091 FCS-3092		FCS-3093	FCS-3094		
Product Image		Onvir	Onvir			
Name	Panoramic Dome Network Camera, PoE 802.3af, 2-Megapixel, Day & Night	Panoramic Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR	Panoramic Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af,	Panoramic Dome Network Camera, 10 Megapixel, PoE 802.3af, Day & Night,		
			WDR, Vandalproof, Vibrationproof	WDR		
LAN Connection Wireless	10/100Mbps -	10/100Mbps -	10/100Mbps -	10/100Mbps -		
Power Input	DC12V 2A / 802.3af PoE	802.3af PoE	802.3af PoE	DC 12V / 802.3af PoE		
Compression	H.264 / MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG		
Max. Resolution & Frame Rate	1600 x 1200, 15 fps for all resolutions	2592 x 1944, 15 fps for all resolutions	2592 x 1944, 15 fps for all resolutions	3648 x 2736, 7 fps for all resolutions		
Horizontal View Angle	180°	180° (overview area), 109.8° (high detail area)	180° (overview area), 109.8° (high detail area)	180° (overview area), 109.8° (high detail area)		
Sensor	2-Megapixel 1/3.2" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	10-Megapixel 1/2.3" Progressive Scan CMOS		
Lens	Fish-eye lens, f=1.25mm, F2.0	Fixed focal, Fixed iris, Fixed focus, f1.19mm, F2.0	Fixed focal, Fixed iris, Fixed focus, f1.19mm, F2.0	Fixed focal, Fixed iris, Fixed focus, f1.37mm, F2.0		
Minimum Illumination	1.5 lux at F2.0	0.1 lux at F2.0	Color: 0.1 lux B/W: 0.05 lux at F2.0	Color: 0.1 lux at F2.0 B/W: 0.05 lux at F2.0		
shutter (sec)	2~1/40,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000		
IRLED /Type/ Distance	-	-	-	-		
ICR (IR-Cut Filter Removal)	V	-	-	V		
AGC/AWB/AES	V					
Wide Dynamic Range Digital Noise Reduction	- 2DNR	Basic WDR (74 dB) 2DNR	Basic WDR (74 dB) 2DNR	Basic WDR (70 dB) 2DNR		
Privacy Mask	-	-	-	-		
DDNS Support	V	V	V	V		
Operation Temperature	0° ~ 50°C	-10°C ~ 50°C	-20°C ~ 50°C	-10°C ~ 50°C		
Approvals	CE, FCC	CE, FCC, IK08	CE, FCC, IP68, IK10, NEMA 4X, EN50155	CE, FCC		
Audio Codec	G.711 / AAC	-	G.711	G.711		
Audio P/T/Z	2-way (Line-in, Line-out) - / - / Digital: 10x	- Digital Zoom to very high detail available on Software	1-way (Mic-in) Digital Zoom to very high detail available on Software	2-way (Line-in, Line-out) Digital Zoom to very high detail available on Software		
Local storage	Micro SD/SDHC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)		
Cell Phone	3GPP / RTSP	RTSP	RTSP	RTSP		
Web Browswer	IE 7 or above	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime		
Optional Accessories	-	-	-	Mount kit: CAS-2101, Wall Mount kit: CAS-2313, Flush Mount Kit: CAS-3003		
Digital I/O	4DI / 1DO	-		1DI / 1DO		

V=Yes -=No



PTZ Dome Camera

LevelOne PTZ Speed Dome Camera provides full Pan/Tilt/Zoom capabilities, allowing for 360° continuous monitoring or can be set to remote control when the user needs to actively follow a person or object. Moreover, the camera is rugged, with weather-proof housing protecting the camera body against rain and dust. Suitable for monitoring wide open indoor or outdoor applications such as airports, highways or for city security.

	PTZ Dome Camera						
Models	FCS-4041 FCS-4042		FCS-4043	FCS-4044	FCS-4101		
Product Image							
	VE						
Name	PTZ Dome Network Camera, PoE+ 802.3af/at, 2-Megapixel, Outdoor, Day & Night, 18x	PTZ Dome Network Camera, PoE+ 802.3af/at, 2-Megapixel, Outdoor, 30x	PTZ Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, 10x, WDR	PTZ Dome Network Camera, 5-Megapixel, PoE 802.3af, Outdoor, Day & Night, 10x, WDR	PT Dome Network Camera, IR LEDs, PoE 802.3af, 2-Megapixel, Day & Night		
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps	10/100Mbps	10/100Mbps		
Wireless	-	-	-	-	-		
Power Input	PoE-Plus 802.3at / 24VAC (Heater needs powered by 24VAC)	AC24V / 802.3at PoE	DC12V / 802.3af PoE	DC12V / 802.3af PoE	DC12V 1.5A / AC24V / 802.3af PoE		
Compression	H.264 / MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264 High Profile, MJPEG	H.264, MPEG4, MJPEG		
Max. Resolution & Frame	1920 x 1080,	1920 x 1080,	2048 x 1536,	2592 x 1944,	1920 x 1080,		
Rate	30/25 fps at 1920 x 1080; 60/50 fps at 1280 x 720	30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	15 fps at 2592 x 1944; 15 fps at 2048 x 1536; 30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	30 fps at 1920 x 1080; 30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240		
Horizontal View Angle	55.2°(wide) ~ 5.2° (tele) (horizontal)	66.4° - 2.61°	49.56 - 5.62°	49.69 - 5.83°	62°		
Sensor	2-Megapixel 1/2.8" Progressive Scan CMOS	2-Megapixel 1/2.8" Progressive Scan CMOS	3-Megapixel 1/3" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	2-Megapixel 1/2.7" Progressive Scan CMOS		
Lens	Auto-iris, Auto focus, f = 4.7 ~ 84.6 mm, F1.6 (wide), F2.8(tele), focus range: 1 m (wide), 1m (tele) to infinity	Zoom, DC iris, Auto focus, f4.3-129mm, F1.6-5.0	Zoom, DC iris, Auto focus, f4.9-49mm, F1.8-3.0	Zoom, DC iris, Auto focus, f4.9-49mm, F1.8-3.0	Board lens, Fixed-focal, f=4.0 mm, F2.0		
Minimum Illumination	0.3 Lux / F1.6 (Color) 0.04 Lux / F1.6 (B/W)	0.1 Lux / F1.6 (Color) 0.05 Lux / F1.6 (B/W)	0.1 Lux / F1.8 (Color) 0.05 Lux / F1.8 (B/W)	0.1 Lux / F1.8 (Color) 0.05 Lux at F1.8 (B/W)	1.0 Lux / F2.0 1/30 ~ 1/120 (Indoor)		
shutter (sec)	1/30~1/30,000 (NTSC) 1/25~1/30,000 (PAL)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/5 ~ 1/10,000	1/30 ~ 1/1,000,000 (Outdoor)		
IRLED /Type/ Distance	-	-	-	-	V (10m)		
ICR (IR-Cut Filter Removal)	V	V	V	V	V		
AGC/AWB/AES	V	V	V	V	V		
Wide Dynamic Range	Basic WDR (74 dB)	Extreme WDR (145 dB)	Superior WDR (110 dB)	Basic WDR (74 dB)	Basic WDR (74 dB)		
Digital Noise Reduction	2DNR/3DNR	2DNR/3DNR	2DNR	2DNR	2DNR		
Privacy Mask	V	V	-	-	-		
DDNS Support	V	V	V	V	-		
Operation Temperature	-10°~50°C (PoE-Plus) -40°~50°C (AC 24V)	-40°C ~ 50°C	-20°C ~ 50°C	-20°C ~ 50°C	0°C ~ 40°C		
Approvals	CE, FCC, IP66, RoHS	CE, FCC, IP67, IK09, NEMA 4X	CE, FCC, IP67, NEMA 4X	CE, FCC, IP67, NEMA 4X	CE, FCC		
Audio Codec	G.711 / G.726 ADPCM/AAC	G.711	G.711	G.711	AMR / AAC		
Audio	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)	2-way (Line-in, Line-out)		
P/T/Z	360° continuous /-10°~ +190° / Optical: 18x	360° / -20° ~ 200°/ Optical: 30X, Digital: 16X	-175° ~ 175° / 0° ~ 180° / Optical: 10X	-175° ~ 175° / 0° ~ 180° / Optical: 10X	200° / 70° / -		
Local storage	Micro SD/SDHC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC/MicroSDXC card slot (card not included)	MicroSDHC card slot (card not included)		
Cell Phone	3GPP/ RTSP	RTSP	RTSP	RTSP	3GPP/ RTSP		
Web Browswer	IE/Safari (Mac/iOS)/Firefox/Chrome	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 6.x or above/Firefox/Chrome/ Safari		
Optional Accessories	Wall Mount kit: CAS-3222/CAS-3223/CAS-3281 Pole Mount kit: CAS-3261/CAS-3263 Ceiling Mount kit: CAS-3241/CAS-3242 Outdoor Power Box: CAS-3291/CAS-3292	Wall Mount Bracket: CAS-4312	Mount kit: CAS-2101, Flush Mount kit: CAS-3004	Mount kit: CAS-2101, Flush Mount kit: CAS-3004	-		
Digital I/O	4DI / 2 DO	4DI / 2 DO	1DI / 1DO	1DI / 1DO			

The LevelOne Home & Small Office IP network camera series

We are putting the power of home and office surveillance in your hands. LevelOne offers all the products you need to build a reliable system to monitor your home: wired, wireless, pan/tilt/zoom, as well as indoor and outdoor options. In addition, our cameras come with free 64-channel surveillance software that enables the user to view, manage, and capture streaming images from any location with an internet connection.

Applications

Surveillance of a small office: meeting rooms, back door and garage. Surveillance of your house: entrance area (front door, intercom), baby's room, bedrooms, as well as effectively securing areas with limited visibility or monitoring a vacation property. Make a visual circuit with potential rental customers at the same time.



Offices

Easy installation is essential

All LevelOne IP cameras contain an installation wizard to help you get started. Only a few clicks and you get access to live pictures in high resolution. Equipped with the newest technology, audio/video streams are transferred into real time. Bundled with the 64-channel software, you can supervise and configure up to 64 cameras at the same time

Living Room



Users can set up motion-detection regions with LevelOne network cameras, each with adjustable size and sensitivity. When motion is detected at the specified regions, the system can send an E-mail alert or send captured images via FTP upload to a designated storage server.



Keep an eye on your home while away



Fixed Camera

With a LevelOne home/small office fixed IP camera, users can easily set up 24/7 security and surveillance in different applications for different needs, monitoring any specified area to prevent unwelcome entry. The FCS-0071 features a fish-eye lens for 180° panoramic view (wall mount) or 360° surround view (ceiling/floor/table mount) without blind spots which enables customer to significantly reduce the need for multiple camera installations.

	Fixed	Panoramic Camera	
Models	FCS-0032	FCS-0051	FCS-0071
Product Image			
Name	Fixed Network Camera, 3-Megapixel, PoE 802.3af	Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR	Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps
Wireless	-	-	-
Power Input	802.3af PoE	802.3af PoE	DC12V 2A / 802.3af PoE
Compression	H.264 Hihg Profile / MJPEG	H.264 High Profile, MJPEG	H.264. MJPEG
Max. Resolution & Frame	2048 x 1536, 15 fps at 2048 x 1536;	2592 x 1944, 15 fps at 2592 x 1944;	1600 x 1200, 30/25 fpsat 1280 x 720
Rate	30 fps at 1920 x 1080; 30 fps at 1280 x 720;	15 fps at 2048 x 1536; 30 fps at 1920 x 1080;	
	30 fps at 640 x 480; 15 fps at 320x240	30 fps at 1280 x 720; 30 fps at 640 x 480; 15 fps at 320 x 240	
Horizontal View Angle	70.8°	92.6°	360°
Sensor	3-Megapixel 1/3.2" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS	2-Megapixel 1/3" Progressive CMOS
Lens	Fixed focal, Fixed iris, Fixed focus, f3.6mm, F2.0	Fixed focal, Fixed iris, Manual focus, f2.8mm, F2.0,	Fish-Eye Lens Focal Length: F2.0 /f = 1.25 mm
Minimum Illumination	0.1 lux at F2.0	0.1 lux at F2.0	1.5lux at F2.0
shutter (sec)	1/5 ~ 1/10,000	1/5 ~ 1/10,000	2~ 1/40,000
IRLED /Type/ Distance		-	-
ICR (IR-Cut Filter Removal)	-	-	V
AGC/AWB/AES	V	V	V
Wide Dynamic Range	-	Basic WDR (74 dB)	-
Digital Noise Reduction	2DNR	2DNR	2DNR
Privacy Mask	-	-	-
DDNS Support	V	V	V
Operation Temperature	-10°C ~ 45°C	-10°C ~ 45°C	0°C ~ 50°C
Approvals	CE, FCC	CE, FCC	CE, FCC
Audio Codec	G.711	G.711	G.711 / ACC
Audio	-	2-way (Built-in Microphone, Line-out)	2-way (Line-in, Line-out)
P/T/Z	Digital Zoom to very high detail available on Software	Digital Zoom to very high detail available on Software	- / - / Optical: 10x
Local storage	-	MicroSDHC/MicroSDXC card slot (card not included)	Micro SD/SDHC card slot (card not included)
Cell Phone	RTSP	RTSP	3GPP / RTSP
Web Browswer	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 8, IE 9, IE 10, IE 11, Firefox with VLC, Chrome with VLC, Safari with Quicktime	IE 7.0 above
Optional Accessories	-	-	-
Digital I/O	-	-	1DI / 1DO

V=Yes -=No

PT Camera

LevelOne Offers wired and wireless PT cameras for users to monitor a home or office from distant locations at any time. Users can easily alter their monitoring angle or area with a mobile phone (PDA, Smart phone), and with the help of Infrared Illuminator LED, users are able to survey a wide range of targets even in total darkness.

	PT Camera				
Models	FCS-6020	WCS-6020	WCS-6050		
Product Image					
Name	PT Network Camera, Day & Night, PoE 802.3af, IR LEDs, 2-Megapixel	PT Network Camera, IR LEDs, 150Mbps 802.11b/g/n, 2-Megapixel, Day & Night	PT Network Camera, IR LEDs, 150Mbps 802.11b/g/n, 5-Megapixel, Day & Night		
LAN Connection	10/100Mbps	10/100Mbps	10/100Mbps		
Wireless	-	802.11b/g/n	802.11b/g/n		
Power Input	DC12V 1.5A	DC12V 1.5A	DC12V 1.5A		
Compression	H.264, MPEG4, MJPEG	H.264, MPEG4, MJPEG	H.264, MJPEG		
Max. Resolution & Frame Rate	1920 x 1080, 30 fps at 1920x1080	1920 x 1080, 30 fps at 1920x1080	2560 x 1920, 10 fps at 2560x1920; 30 fps at 1920x1080		
Horizontal View Angle	62°	62°	62°		
Sensor	2-Megapixel 1/2.7" Progressive Scan CMOS	2-Megapixel 1/2.7" Progressive Scan CMOS	5-Megapixel 1/3.2" Progressive Scan CMOS		
Lens	Board lens, fixed-focal, f=4.0 mm, F2.0	Board lens, fixed-focal, f=4.0 mm, F2.0	Board lens, fixed-focal, f=4.0 mm, F2.0		
Minimum Illumination	Color: 1.5 lux at F2.0 B/W: 1.0 lux at F2.0	Color: 1.5 lux at F2.0 B/W: 1.0 lux at F2.0	Color: 1.5 lux at F2.0 B/W: 1.0 lux at F2.0		
shutter (sec)	1 ~ 1/10,000	1 ~ 1/10,000	1 ~ 1/10,000		
IRLED /Type/ Distance	V (10m)	V (10m)	V (10m)		
ICR (IR-Cut Filter Removal)	V	V	V		
AGC/AWB/AES	V	V	V		
Wide Dynamic Range	-	-	-		
Digital Noise Reduction	2DNR	2DNR	2DNR		
Privacy Mask	-	-	-		
DDNS Support	V	V	V		
Operation Temperature	0°C ~ 40°C	0°C ~ 40°C	0°C ~ 40°C		
Approvals	CE, FCC	CE, FCC	CE, FCC		
Audio Codec	G.711 / AMR	G.726 / AMR	G.711 / AMR		
Audio P/T/Z	2-way (Built-in Microphone, Line-out) 355° / 135°/-	2-way (Built-in Microphone, Line-out) 355° / 135°/-	2-way (Built-in Microphone, Line-out) 355° / 135°/-		
Local storage	SD/SDHC card slot & USB port (card not included)	SD/SDHC card slot & USB port (card not included)	SD/SDHC card slot & USB port (card not included)		
Cell Phone	3GPP / RTSP	3GPP / RTSP	3GPP / RTSP		
Web Browswer	IE 6.x or above/Firefox/Chrome/Safari	IE 6.x or above/Firefox/Chrome/Safari	IE 6.x or above/Firefox/Chrome/Safari		
Optional Accessories	-	-	-		
Digital I/O	1DI / 1DO	1DI / 1DO	1DI / 1DO		

V=Yes -=No

1. View your camera by http://camera_IP_Add:8008 2. View your camera by http://camera_IP_Add/img/mjpeg.htm 3. Java and QuickTime is required



Lens

LevelOne offers a variety of optional C/S mount lenses for diverse monitoring conditions, or to meet any special surveillance requirement



CAS-1200 3~8mm Vari-focal Lens

- Sensing Area: 1/3" CCD
- Iris: DC-drive Auto Iris
- Diagonal: 118.7°~44.1°
- Horizontal: 93.4°~34.6°
- Vertical: 68.7°~26.0°



CAS-1300 2.8~8.5mm Vari-focal Day/Night Megapixel Lens

- Sensing Area: 1/3" CCD
- Iris: DC-drive Auto Iris
- Diagonal: 118.1°~41.7°
- Horizontal: 95.4°~33.5°
- Vertical: 71.3°~25.0°

Outdoor Enclosure

The LevelOne Outdoor Enclosure is an excellent addition to any surveillance network, providing superior outdoor performance



BOH-1400 Camera PoE Outdoor Enclosure

- Weatherproof IP66-rated with wide operating temperature (-20°C to 50°C) for harsh environments
- Vandal-proof IK10-rated housing
- Power support: High Power PoE
- Works with LevelOne POI-4000 & FSW-0513



BOH-1401 Camera PoE Outdoor Enclosure, IR LEDs

- Weatherproof IP66-rated with wide operating temperature (-20°C to 50°C) for harsh environments
- Vandal-proof IK10-rated housing
- Built-in infrared LEDs for night viewing up to 50m
- Power support: High Power PoE
- Works with LevelOne POI-4000 & FSW-0513



BOH-1410 Camera PoE Outdoor Enclosure, FEVE Coating

- FEVE coating application enhance UV and acid protection
- Weatherproof IP66-rated with wide operating temperature (-20°C to 50°C) for harsh environments
- Vandal-proof IK10-rated housing
- Power support: High Power PoE
- Works with LevelOne POI-4000 & FSW-0513



BOH-1411 Camera PoE Outdoor Enclosure, IR LEDs, FEVE Coating

- FEVE coating application enhance UV and acid protection
- Weatherproof IP66-rated with wide operating temperature (-20°C to 50°C) for harsh environments
- Vandal-proof IK10-rated housing
- Built-in infrared LEDs for night viewing up to 50m
- Power support: High Power PoE
- Works with LevelOne POI-4000 & FSW-0513



DOH-1000 Domed Outdoor Housing

- Designed for Indoor/outdoor applications
- IP66 rated camera outdoor dome housing
- Lightweight for Mounting on the wall
- Easy access for service and installation
- Withstands severe weather
- Low Cost




DOH-1100 Heavy-Duty Domed Outdoor Housing

- Heavy-duty aluminium dome for outdoor and indoor installation
- 2-layer dome design keeps cameras cool
- Special fluorocarbon coating resists harsh acids and bases (i.e. salt water)
- Auto-sensing fan and heater for internal temperature control
- Vandal-proof polycarbonate cover
- IP-66 rated protection level

Optional Accessories

LevelOne offers a wide range of optional accessories to help users set up a complete IP surveillance solution.







Model: CAS-3221 Description: Corner Plate Mini Works with: FCS-3081



Model: CAS-3222 Description: Corner Plate Mount Works with: FCS-4041



Model: CAS-3223 Description: Corner Thin Box Mount Works with: FCS-4041



Model: CAS-3241 / CAS-3242 Description: Straight Tube (25cm/50cm) Works with: FCS-3081/FCS-4041



Model: CAS-3261 Description: Pole Thin Direct Mount Works with: FCS-3081/FCS-4041



Model: CAS-3263 Description: Pole Thin Box Mount Works with: FCS-4041



Model: CAS-3281 Description: Wall Box Mount Works with: FCS-4041



Model: CAS-3291 Description: Outdoor Power Box (110-115V AC) Works with: FCS-4041



Model: CAS-3292 Description: Outdoor Power Box (220-230V AC) Works with: FCS-4041



Model: CAS-4001 Description: Pole Mount Kit for Outdoor Camera Enclosure Works with: BOH-1400/BOH-1401/ BOH-1410/BOH-1411



Model: CAS-4200 Description: USB Joystick for P/T/Z Network Camera Works with: FCS-4041



Model: CAS-3030 Description: IR Illuminator (30m,80° view angle, IP66 Housing)



Model: CAS-3300 Description: Ceiling Bracket Works with: FCS-5055/FCS-5065



Model: CAS-4312 Description: Wall Mount Bracket, Cable Management Works with: FCS-4042

Powerful Surveillance Management Software

LevelOne has developed intelligent and advanced surveillance management software that complements our digital IP Surveillance Cameras. The highend freeware offers advanced features such as Missing Object and Foreign Object, whereby the camera can detect if something is missing from a regular image and sound an alarm, or if something is added to a viewing area that should not be there such as a bag, box car or person. The freeware version can be upgraded to support 100 channels for a small subscription fee.

The Central Management Software (CMS) included in LevelOne's freeware bundle allows users to link and manage a network of NVRs. By purchasing additional CMS licences and connecting multiple NVRs, users can scale a network up to any size required.

Other capabilities include H.264 compression to reduce the storage bandwidth of megapixel cameras, Pan/Tilt/Zoom functions and 2-Layer E-Map to identify the location of all cameras in the network, whereby an E-Map will pop-up on the host computer with the exact location of a security breach. LevelOne's security solutions can also be monitored remotely via iOS and Android apps.

LevelOne's TV Wall Management System enables robust viewing of multiple cameras from the central management point, displaying multiple views from different sources on the one easy interface. Rather than relying on an operator increasing resolution or switching between screens to effectively monitor multiple cameras, TV Wall Management System allows greater control and operational efficiency through a single pane-of-glass.

Advantages of LevelOne OneSecure Video Management Software

- Free bundle 64 Channels. License fee is required to unlock additional channel Maximum up to 100 Channels total.
- Recording up to 100 Channels
- Live view local up to 100 Channels, remote up to 100 Channels
- Synchronized playback local up to 100 Channels
- Export video with RAW and AVI formats
- Event trigger, response and notification
- Mobile Client, Web Client, Workstation
- Location-based management with eMap
- Smart search function
- Non-Level1 camera supported via licensed Camera Device Pack license fee is required

Instant Actions and Notifications

The software has several notification features that enable a surveillance system to monitor and report on certain activities. Actions and notifications include Pop-up window with live video, switch to hotspot window, play beep sound, activate external device through digital output, upload snapshot to FTP server, execute system command to activate other programs, e-mail notification with snapshots, and command a PTZ device to go to a preset point.

Improve Image Quality

The management software includes several important image enhancing features to get better quality when recorded images are played back. The video enhancement tool is crucial for investigating security-related imagery when it comes to face and object recognition.

Quadruple Monitoring Function works with CMS and TV wall

This feature enables the software to display a wide array of cameras. On one screen up to 64 channels can be viewed simultaneously, while the other screen only displays selected cameras, allowing quick or priority monitoring. The other screens can also be used to playback recorded segments while the first screen maintains live viewing capability. TV Wall functionality is available by purchasing LevelOne's TV Wall Management System.



FCS-9364 FCS-9300 FCS-9310

4 OneSecure Video Management Software, 64-Channel
0 Central Management System
0 TV Wall Management System

Multi-Vendor

LevelOne offers paid service for integrating OneSecure software to support non-LevelOne cameras.

*All company names, brand names, trademarks and logos are the property of their respective companies.



level

one


OneSecure

OneSecure is a new, free-launch iOS / Android application that enables users to remotely monitor live video camera through LevelOne OneSecure Surveillance Systems. View of up to 64 cameras through LevelOne OneSecure software over a Wi-Fi/3G or 4G network. NVR (NVR-12xx) can be connected as well.



E-Map

The E-Map gives users an overview of the surveillance system and helps to locate each camera. If an incident occurs, such as an intruder alert, the related camera will be highlighted and users can switch to this camera immediately.



21

OneSecure Video Management Software

The LevelOne OneSecure software series has been developed by LevelOne to provide more advanced features for digital surveillance systems. The OneSecure solution provides full camera control and support for all LevelOne cameras as well as devices from other manufacturers.

General		(DneSecure			
ull Name			o Management Software			
Maximum Number of Clients			emote (concurrent)			
Maximum Number of Cameras			100			
ree License		6	4 channels			
Compression			MPEG-4, MJPEG			
ive View						
isplay Layout Mode		Local display:	1, 4, 5, 6, 8, 9, 10, 12, 16			
isplay Layout Mode			8, 9, 10, 12, 16, 18, 24, 25, 35, 36, 48, 49, 64			
'iew Manager			re-set cameras within layout in the public or private view			
iew Patrol			ween different views or devices			
iew Panel			e-defined views for quick launch			
evice Panel			e panel into display layout; display camera status			
Digital Zoom			e scroll wheel or by zoom control buttons			
Ngital 20011 Nanual Recording / Snapshot			Instant snapshot upon mouse click or hot key			
	Disalau avanta	5 1				
vent Panel			covery between server and client or when the allocated disk space is full			
wo-way Audio	Auc		evices; audio broadcast to multiple devices at the same time			
Dual Stream Management			r stream 2 of dual stream devices			
nstant Playback		Instant playba	ack in live view window			
-Мар						
ayout			s, small live view windows; hyperlinked			
etup	e-Map ima		d pointed direction of camera; view positioning; source positioning			
TZ Mode	l	Mouse PTZ mode to	control e-Map video streams			
TZ						
ontrol		Pan, tilt and zoom controls; speed	control; both buttons and overlay controls			
reset Points and Tours		Create preset points; creat	te auto tours between preset points			
lumber of Preset Points			32			
oystick			l joystick supported			
upport Protocol		Auto-detect camera's PTZ protocol. Avai	lable protocols: Pelco-P, Pelco-D, Dynacolor, Visca			
Recording						
cheduled Recording		Record video w	ith user defined schedule			
vent Recording		Record video when the alarm event is tric	gered, including the pre-event buffered video clip			
peed Up			ettings for non-event and triggered event			
Nanual Recording		· · · · · · · · · · · · · · · · · · ·	ding upon mouse click			
Pre-Event Recording			re event occurs. The maximum buffer is 5 seconds			
Post-Event Recording			event occurs. The maximum buffer is 300 seconds			
Dual Stream Management	Recording of stream 1 or stream 2 of dual stream devices					
Search & Playback		hecording of stream re				
Recording Search	Soarch vie	lea recordings by time, event, channel and liste	d as clickable thumbnails for full-size view and snapshot download			
Playback Control	Jearch vic		vith speeds 1x/2x/4x/8x or frame-by-frame; pause; stop			
			· · · · · · · · · · · · · · · · · · ·			
Synchronized Playback	100 channels					
Manual Chanchat	Instant snapshot from playback upon mouse click					
· · ·		· · ·				
Digital Zoom		Zoom in/out digita	lly by PiP (Picture-in-Picture)			
Digital Zoom /ideo Export		Zoom in/out digita				
Digital Zoom /ideo Export Event Management		Zoom in/out digita Export video clips in AVI or	lly by PiP (Picture-in-Picture) RAW format; text overlay supported			
Vanual Snapshot Digital Zoom Video Export Event Management Event Trigger	Video motion	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr	lly by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery;			
Digital Zoom /ideo Export Event Management Event Trigger		Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc	lly by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found			
Digital Zoom /ideo Export Event Management Event Trigger	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output;			
Digital Zoom /ideo Export Event Management	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma	lly by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots;			
Digital Zoom Video Export Svent Management Svent Trigger Svent Response	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc p-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager			
Digital Zoom Video Export Event Management Event Trigger	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling System Permission Control	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager			
Digital Zoom Video Export Event Management Event Trigger Event Response Vanual Event Event Handling Evernission Control Language	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups			
Digital Zoom Video Export Event Management Event Trigger Event Response Vanual Event Event Handling Evermission Control anguage anguage Import/Export	Record video; Pop	Zoom in/out digita Export video clips in AVI or Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-Ic Possibility to import or export language	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling Event Mandling	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling Event Handling Evermission Control .anguage .anguage Import/Export Eustomizable User Interface Quick Setup	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback			
Digital Zoom Video Export Vent Management Vent Trigger Vent Response Manual Event Vent Handling Vystem Vermission Control anguage anguage Import/Export Lustomizable User Interface Quick Setup Remote Access	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR			
Digital Zoom /ideo Export Event Management Event Trigger Event Response Manual Event Event Handling System Permission Control .anguage .anguage Import/Export Customizable User Interface Quick Setup Remote Access PC Client Program	Record video; Pop	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup			
Digital Zoom Video Export Vent Management Vent Trigger Vent Response Vent Response Vent Handling Vert Handling Vert Handling Vert Solution anguage anguage Import/Export Customizable User Interface Quick Setup Remote Access CC Client Program CC Web Browser	Record video; Pop Upload :	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR eview, PTZ, playback, e-Map, event management, setup , PTZ, playback, e-Map, event management, setup			
bigital Zoom fideo Export ivent Management vent Trigger vent Response Aanual Event vent Handling iystem ermission Control anguage anguage Import/Export iustomizable User Interface Quick Setup temote Access C Client Program C Web Browser	Record video; Pop Upload :	Zoom in/out digita Export video clips in AVI or Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback			
bigital Zoom fideo Export vent Management vent Trigger vent Response Aanual Event vent Handling ystem ermission Control anguage anguage Import/Export ustomizable User Interface Quick Setup temote Access C Client Program C Web Browser Aobile Client Program	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-L Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback te, iPad, iTouch and Android device			
Digital Zoom Video Export Vent Management Vent Trigger Vent Response Aanual Event Vent Handling Vermission Control Aanguage Aanguage Import/Export Customizable User Interface Quick Setup Vermote Access PC Client Program PC Web Browser Aobile Client Program Display Mode	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Minimum	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback le, iPad, iTouch and Android device Recommended			
Digital Zoom Video Export Event Management Event Trigger Event Response Manual Event Event Handling System Permission Control a.anguage anguage Import/Export Eustomizable User Interface	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback e, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM			
Digital Zoom Video Export Vent Management Vent Trigger Vent Response Anual Event Vent Handling Vystem Vermission Control anguage anguage Import/Export Customizable User Interface Quick Setup Vermote Access PC Client Program CC Web Browser Aobile Client Program Display Mode Verver PC with Local Client	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback ie, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i7-920 2.67 GHz, 4GB RAM			
Digital Zoom Video Export Vent Management Vent Management Vent Trigger Vent Response Anual Event Vent Handling Vermission Control anguage anguage Import/Export Customizable User Interface Quick Setup Remote Access CC Client Program CC Client Program CC Client Program CC Dient Program Display Mode Verver PC with Local Client Verver PC without Local Client	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or Getection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Gore 2 Quad 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR eview, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback live, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM			
Digital Zoom Video Export Vent Management Vent Trigger Vent Response Anual Event Vent Handling Vystem Vermission Control anguage anguage Import/Export Customizable User Interface Quick Setup Vermote Access PC Client Program CC Web Browser Aobile Client Program Display Mode Verver PC with Local Client	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM			
Digital Zoom fideo Export vent Management vent Trigger vent Response Aanual Event vent Handling vermission Control anguage anguage Import/Export ustomizable User Interface Duick Setup Remote Access CC Client Program CC Client Program CC Web Browser Aobile Client Program Display Mode erver PC with Local Client iermote Client PC	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or Getection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-li Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM			
higital Zoom ideo Export vent Management vent Trigger vent Response Aanual Event vent Handling ystem ermission Control anguage anguage Import/Export ustomizable User Interface Quick Setup emote Access C Client Program C Web Browser Aobile Client Program Display Mode erver PC with Local Client erver PC without Local Client emote Client PC C Operating System	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system command Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel is 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel S 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Net S 2.4 GHz, 4GB RAM			
higital Zoom ideo Export vent Management vent Trigger vent Response Aanual Event vent Handling ystem ermission Control anguage anguage Import/Export ustomizable User Interface Quick Setup emote Access C Client Program C Web Browser Aobile Client Program Display Mode erver PC with Local Client erver PC without Local Client emote Client PC C Operating System	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system command Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel is 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel S 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup ts live view, PTZ control, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM			
bigital Zoom ideo Export vent Management vent Trigger vent Response Manual Event vent Handling ystem ermission Control anguage anguage Import/Export iustomizable User Interface Quick Setup emote Access C Client Program C Web Browser Nobile Client Program Display Mode erver PC with Local Client erver PC without Local Client erver PC without Local Client erver PC without Local Client erver PC without Local Client erver C Web Browser C Operating System C Web Browser	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or detection; Passive IR sensor; External device thr Server loss and reco o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system command Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel is 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel S 2.4 GHz, 4GB RAM	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM News 8, Windows Server 2012			
Digital Zoom Video Export Vent Management Vent Management Vent Trigger Vent Response Anual Event Vent Handling Vermission Control anguage anguage Import/Export Customizable User Interface Quick Setup Remote Access CC Client Program CC Client Program CC Client Program CC Dient Program Display Mode Verver PC with Local Client Verver PC without Local Client	Record video; Pop Upload : 	Zoom in/out digita Export video clips in AVI or Getection; Passive IR sensor; External device thr Server loss and recc o-up window with live video; Switch to hotspot snapshot to FTP server; Execute system comma Command a PTZ d Manually activate external devices Define the sch Unlimited number of users, Active Dire Multi-la Possibility to import or export language Define the layout of user Configure User interface program (Workstation) with live Microsoft Internet Explorer with live view levice application (Active Mobile Client) suppor Supported devices: iPhor Minimum Intel Core 2 Quad 2.4 GHz, 4GB RAM Intel is 2.4 GHz, 4GB RAM Intel replorer 8, Internet Explorer 8, Inter	Ily by PiP (Picture-in-Picture) RAW format; text overlay supported ough digital input; Video loss and recovery; Network loss and recovery; very; Disk full; Disk not found window; Play beep sound; Activate external device through digital output; nd to activate other programs; E-mail notification with snapshots; evice to go to a preset point through digital output via live view monitor edule of event manager ctory, Customizable permissions for user groups anguage support packs for convenient local language management interface for live view and playback basic settings of NVR e view, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event management, setup t, PTZ, playback, e-Map, event or time based search and playback te, iPad, iTouch and Android device Recommended Intel i5 2.4 GHz, 4GB RAM Intel i5 2.4 GHz, 4GB RAM News 8, Windows Server 2012			

* These specifications are based on following camera settings: Single stream mode: 1280x1024, 3Mbps, 18fps, MPEG-4 Dual stream mode:

Stream 1: 1280x1024, 3Mbps, 18fps, H.264

Stream 2 : 640x480, High Quality, 18fps, MJPEG

For more details about system requirements, please refer to Project Planner on http://global.level1.com/

Network Video Recorders



Simple set up and a reliable, cost-effective surveillance system

The LevelOne Network Video Recorder (NVR) series is compatible with LevelOne network cameras, and offers a complete recording solution. It enables live view recording and playback for up to 16 IP network cameras via the local area network or over the Internet simultaneously. No specific software is required, just plug the NVR into your LAN connected device (switch or router) and with a few clicks it will search and configure each connected Network Camera instantly. It allows users to easily build an advanced surveillance network.

Network Video Recorder (NVR)

The Network Video Recorder (4/9/16-Channel) is designed to suit your needs. It enables HDMI local display and recording up to 10MP resolution. NVR includes free bundled software –no additional licensing.

Model	NVR-1204	NVR-1209	NVR-1216
Product Image			
Name	Network Video Recorder, 4-Channel	Network Video Recorder, 9-Channel	Network Video Recorder, 16-Channel
Product Type	Standalone NVR	Standalone NVR	Standalone NVR
Maximum Number of Cameras	4	9	16
Maximum Number of Clients	1 local, 2 remote	1 local, 2 remote	1 local, 2 remote
Free License	4	9	16
Video Resolution	Up to 4-Megapixel (Local display), Up to 10- Megapixel (Remote display)	Up to 4-Megapixel (Local display), Up to 10- Megapixel (Remote display)	Up to 4-Megapixel (Local display), Up to 10- Megapixel (Remote display)
Compression	H.264	H.264	H.264
Multi-Streaming	Dual streams	Dual streams	Dual streams
Network Connector	RJ-45	RJ-45	RJ-45
Scheduled Recording	V	V	V
Event Recording	V	V	V
Manual Recording	V	V	V
Speed Up	V	V	V
Recording Throughput	16 Mbps	36 Mbps	48 Mbps
HDD Interface	Maximum 2 SATA disks; Options to have empty bays or one 1TB storage disk included	Maximum 2 SATA disks; Options to have empty bays or one 1TB storage disk included	Maximum 2 SATA disks; Options to have empty bays or one 2TB storage disk included
Display Layout Mode	Local: 1, 2, 4 Remote: 1, 2, 4	Local: 1, 2, 4, 9, 1+5, 1+7, 2+4 Remote: 1, 2, 4, 9, 1+5, 1+7, 2+4	Local: 1, 2, 4, 9, 12, 16, 1+5, 1+7, 1+12, 2+4, 2+8 Remote: 1, 2, 4, 9, 12, 16, 1+5, 1+7, 1+12, 2+4, 2+8
Digital Zoom	V	V	V
Event Status	Display event status upon alarm or upon connection	Display event status upon alarm or upon connection	Display event status upon alarm or upon connection
	loss or recovery between server and client	loss or recovery between server and client	loss or recovery between server and client
Instant Playback	Instant Playback in live view window (Remote client)	Instant Playback in live view window (Remote client)	Instant Playback in live view window (Remote client)
PTZ Control	V	V	V
Playback Control	Continuous forward and backward playback with speeds 0.5x/1x/2x/4x/8x/16x/32x; pause; stop	Continuous forward and backward playback with speeds 0.5x/1x/2x/4x/8x/16x/32x; pause; stop	Continuous forward and backward playback with speeds 0.5x/1x/2x/4x/8x/16x/32x; pause; stop
Synchronized Playback	4 channels	9 channels	16 channels
Local Access	HDMI monitor, USB keyboard & mouse	HDMI monitor, USB keyboard & mouse	HDMI monitor, USB keyboard & mouse
Remote Access	Web Client (IE), Mobile Client (iOS & Android)	Web Client (IE), Mobile Client (iOS & Android)	Web Client (IE), Mobile Client (iOS & Android)
Event Trigger	Video motion detection; External device through digital input; Network loss and recovery	Video motion detection; External device through digital input; Network loss and recovery	Video motion detection; External device through digital input; Network loss and recovery
Event Response	Record video; Beep; Digital output; E-mail with snapshots; Event logging; Go to PTZ preset point	Record video; Beep; Digital output; E-mail with snapshots; Event logging; Go to PTZ preset point	Record video; Beep; Digital output; E-mail with snapshots; Event logging; Go to PTZ preset point
Permission Control	Unlimited number of users, Customizable permissions for user groups	Unlimited number of users, Customizable permissions for user groups	Unlimited number of users, Customizable permissions for user groups
Video Export	USB	USB	USB
Server Operating System	Embedded Linux	Embedded Linux	Embedded Linux
Client PC Operating System	Windows 8, Windows 7	Windows 8, Windows 7	Windows 8, Windows 7
PC Web Browser	IE 9, IE 10, IE 11	IE 9, IE 10, IE 11	IE 9, IE 10, IE 11
ONVIF Compliant	-	-	-
Operating Temperature	0°C ~ 40°C (32°F ~ 104°F)	0°C ~ 40°C (32°F ~ 104°F)	0°C ~ 40°C (32°F ~ 104°F)
Approvals	CE, FCC	CE, FCC	CE, FCC




Integrating Analog Cameras into IP Security Surveillance Networks

As more and more security networks are making the move from analog to digital, there are many people that are stuck in the middle. What do you do if you just purchased a CCTV system, yet you want the flexibility and functionality of digital surveillance? LevelOne's Video Server and Capture Cards are the answer. By integrating your existing CCTV cameras into a feature-rich digital network, you can hold onto the previous investment while taking advantage of new technology.










FCS-9364 OneSecure Video Management Software

Analog Camera

Hybrid Interoperable

LevelOne provides surveillance products that enable already-installed analog surveillance products to be integrated into a digital IP-based surveillance system.



Related Products



- 4 channels up to 30fps in D1 resolution per channel - total 120fps (FCS-7004)
- Real time H.264 High profile, MJPEG compression
- Dual Stream simultaneously
- Powered by DC12; 802.3af
- 2 Way Audio (Line in, Line out) - DI/DO X4(FCS-7004)

- functions
- View up to 120 frames per second
- Superior video resolution up to
- 704 x 480 (NTSC)/704x576 (PAL)
- 2 ports audio inputs
- MPEG-4 compression mode
- Supports Windows XP/Server 2003/Vista/7
- MPEG-4 compression mode - Supports Windows XP/Server 2003/Vista/7

- View up to 120 (NTSC)/100 (PAL) frames per

- Superior video resolution up to

- 4 ports audio inputs


704 x 480 (NTSC)/704x576 (PAL)

second



Installation over PoE Network by PoE Switch

For a powerless environment, LevelOne recommends the deployment of a Cat.5 (or above) Ethernet LAN by using our PoE switches. The switches provide PoE ports that can connect directly to our PoE-enabled network cameras over a 100m distance. This is an excellent solution to deploy together with power redundancy to ensure constant power supply in case of failure.



PoE switch with IEEE 802.3af compliant

Model	FSW-0503	IFE-0500	IFE-0501	IFE-0502	GEP-0520
PoE Port	4 x 10/100Mbps	4 x 10/100Mbps	4 x 10/100Mbps	4 x 10/100Mbps	4 x 10/100/1000Mbps
PoE Total Budget	61.6W	57W	57W	57W	61.6W

Model FSW-1671 Model FSW-0513 PoE Port 8 x 10/100Mbps PoE Port 4 x 10/100Mbps PoE Total Budget 123.2W PoE Total Budget 120W


PoE switch with IEEE 802.3af/at compliant

Model	GEP-0521	FEP-0811	FEP-0812	GEP-0820	GEP-0821/0822	GEP-0950
			8	C C C C C C C C C C		
PoE Port	4 x 10/100/1000Mbps	8 x 10/100Mbps	4 x 10/100Mbps	8 x 10/100/1000Mbps	8x 10/100/1000Mbps	8 x 10/100/1000Mbps
PoE Total Budget	120W	123.2W	61.3W	61.6W	123.2W/250W	130W

Model	FEP-1611/1612	GEP-1621/1622	GEP-2671/2672	FGP-2410/2412	GEP-2450	GEP-5070
			Бонтонулти	P (111111111		
PoE Port	16 x 10/100Mbps	16 x 10/100/1000Mbps	24 x 10/100/1000Mbps	24 x 10/100Mbps	24 x 10/100/1000Mbps	48 x 10/100/1000Mbps
PoE Total Budget	240W / 480W	240W/480W	185W/370W	240W/486.4W	184.8W	375W

PoE Extender over Hybrid Fiber

Using hybrid fiber and copper cable, the LevelOne PFE range can deliver integrated power and data over a distance of 6,800 ft (2km) to a receiver which provides high-power PoE output for IP surveillance applications. A tough outdoor range (PFE-1011/1014) provides the same performance within a durable IP66-rated waterproof housing for harsh environmental conditions and temperature range of -40°C to 60°C.



PoE Extender over Hybrid Fiber

Model	PFE-1001T	PFE-1101T	PFE-1001R	PFE-1004R
Туре	Tramsmitter	Tramsmitter	Receiver	Receiver
PoE Standard	-	-	Proprietary	Proprietary
Power Output	65W (110-240V AC)	120W (110-240V AC)	-	-
Data Output	1 x 100Mbps LC, 2KM	1 x 100Mbps LC, 2KM	1 x 100Mbps LC, 2KM	1 x 100Mbps LC, 2KM
PoE Output	-	-	1 x 10/100Mbps	4 x 10/100Mbps
PoE Power Budget	-	-	20W~60W for 450M~2KM	20W~60W for 450M~2KM
IP-Rating	-	-	-	-

Model

PFE-1014R

	STATE THE	
Туре	Outdoor Receiver	Outdoor Receiver
PoE Standard	Proprietary	Proprietary
Power Output	-	
Data Output	1 x 100Mbps LC, 2KM	1 x 100Mbps LC, 2KM
PoE Output	1 x 10/100Mbps	4 x 10/100Mbps
PoE Power Budget	20W~60W for 450M~2KM	20W~60W for 450M~2KM
IP-Rating	IP66	IP66

PFE-1011R



Hybrid Cable


Fiber/ Power Distance / PoE Output Table

Mdoel No	Hybrid Cable	Conductor Gauge	450M	700M	1KM	2KM
PFE-1001T	PFC-0112	12 AWG			40W	20W
PFE-1001T	PFC-0118	18 AWG	40W	20W		
PFE-1101T	PFC-0112	12 AWG	60W	55W	50W	28W
PFE-1101T	PFC-0118	18 AWG	50W	28W		



Installation over PoE Network by PoE Repeater

The traditional PoE standard (IEEE 802.3af) supports 15.4W, and normal cable runs only reach 100m, which is fine for regular devices. But what do you do if your network cameras need more power or extend over a greater distance? LevelOne PoE repeaters allow a PoE device to be attached to your network over a distance of up to 800m. The "IN" port accepts the power and data for the first 100m, and the "OUT" port boosts and extends the power and data an additional 100m.




Power over Ethernet (PoE) Repeaters

Model	POR-0100	POR-0102	POR-1100	POR-1102
	The second secon		A X	N.N.
RJ-45 Output Port	1 x 10/100Mbps	2 x 10/100Mbps	1 x 10/100Mbps	2 x 10/100Mbps
RJ-45 Input Port	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps
RJ-11 Input Port	-	-	-	-
RJ-11 Output Port	-	-	-	-
IP-Rating	-	-	IP65	IP65

Model	POR-0120	POR-0122
		The stand and the second and the sec
RJ-45 Output Port	1 x 10/100/1000Mbps	2 x 10/100/1000Mbps
RJ-45 Input Port	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps
RJ-11 Input Port	-	-
RJ-11 Output Port	-	-
IP-Rating	_	_

Simple yet durable, no software required

As a PoE-Plus Repeater, POR-02xx, POR-12xx series receives all power from the Power Sending Equipment (PSE), for example, a PoE-Plus switch. This means that POR-0200 uses no external power supply, making it the most flexible option for system integrators looking for an easy, affordable solution to increase the distance to the attached devices.



PoE Repeater with IEEE 802.3af/at compliant


Model	POR-0200	POR-0202	POR-1200	POR-
1202		House Madelware Contraction	N N N	N N N
RJ-45 Output Port	1 x 10/100Mbps 1 x 10/100Mbps (LAN)	2 x 10/100Mbps	1 x 10/100Mbps 1 x 10/100Mbps (LAN)	2 x 10/100Mbps
RJ-45 Input Port	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps
RJ-11 Input Port	-	-	-	-
RJ-11 Output Port	-	-	-	-
IP-Rating	-	-	IP65	IP65

Model	POR-0220	POR-0222	POR-1220	POR-1222
			EXX.	T N N
RJ-45 Output Port	1 x 10/100/1000Mbps	2 x 10/100/1000Mbps	1 x 10/100/1000Mbps	2 x 10/100/1000Mbps
	1 x 10/100/1000Mbps (LAN)		1 x 10/100/1000Mbps (LAN)	
RJ-45 Input Port	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps
RJ-11 Input Port	-	-	1 x 10/100Mbps	-
RJ-11 Output Port	-	-	-	-
IP-Rating	-	-	IP65	IP65



Installation over PoE Network by PoE Injector and PoE Splitter

Not all IP devices are equipped with PoE function, however you can still use a single Cat.5 cable to deliver power and data to the IP device, as LevelOne's PoE injectors provide power over a single Ethernet cable. Each output port of the PoE injector combines both data and power through a single Cat.5 cable to the PoE PD(Power Device), and with a PoE Splitter it separates the data and power from a networked PoE signal so it can be used for non-PoE devices installed in places where power is difficult to obtain.



PoE Injector


Model	POI-4000	POI-2002	POI-3002	POI-2001	POI-3000
	And				to a
PoE	V	802.3af	802.3af/at	802.3af	802.3af/at
PoE Output	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps
RJ-45 Input	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100/1000Mbps	1 x 10/100/1000Mbps
PoE Power Budget	56W	15.4W	30W	15.4W	30W

PoE Splitter

Model	POS-4000	POS-4002	POS-1002	POS-3000	POS-4001
	ranama kana kana kana kana Internet	Termina war war Piter	Por	D.	U.V.
PoE	V	V	802.3af	802.3af/at	V
Power Output	3-12V DC	24AC	5-12V DC	5-12V DC	3-12V DC
RJ-45 Input	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100/1000Mbps	1 x 10/100Mbps
RJ-45 Output	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100Mbps	1 x 10/100/1000Mbps	1 x 10/100Mbps
IP Rating	-	-	-	-	IP65

Installation over PoE Network by PoE Injector Hubs

Fully compliant with the IEEE 802.3af standard and acts as a patch panel between a legacy switch and other network devices to provide power and data, including PoE power of up to 30W per port over existing Cat.5 Ethernet cable.




Injector Hubs

Model	POH-1250	POH-1260
PoE	802.3af	802.3af
PoE Port	12 x 10/100Mbps	12 x 10/100Mbps
Ethernet Port	12 x 10/100Mbps	12 x 10/100Mbps
PoE Power Budget	200W	375W



Installation over Wireless Network

LevelOne offers a wide range of wireless network devices to fulfil different surveillance scenarios. For example, monitoring a large area would cost a lot for installation of electrical wiring, but by using LevelOne FCS-5041 + WUA-5600 (High power outdoor USB adapter with 7dBi antenna), this can now be monitored from a central control room or via remote control access over a wireless internet without any electrical wiring fees. In addition, home or small office users can set up a complete surveillance network using a simple network of switches, a wireless Modern Router and Network Video Recorder (NVR).



Wireless Access Points


Model	WAB-5120	WAB-6120	WAP-6101	WAP-6103
		No. Le v		
Wireless Standard	300Mbps (11a/n)	150Mbps (11b/g/n)	300Mbps (11b/g/n)	300Mbps
Antenna/Connector	2 x 16dBi /RP-SMA	1 x 8dBi (Internal) / N-type	2 x 5dBi (Internal) / -	2x 3dBi (internal) / -
PoE	V	V	V	V
Frequency Range	5GHz	2.4GHz	2.4GHz	2.4GHz
Multiple-SSID	16	16	4	8
AP/ AP Client/WDS Mode	V	V	V	V
IP Rating	IP55	IP55	-	-

Antennas

Model	OAN-2090	OAN-2151	WAN-2181	WAN-7100
			0	
Description	Omni-Directional	Omni-Directional	Directional Panel	Directional Dual-Polarization
Frequency Range	2.4GHz	2.4GHz	2.4GHz	2.4GHz
Indoor/Outdoor	Indoor/Outdoor	Outdoor	Outdoor	Indoor/Outdoor
Gain	9 dBi	15 dBi	18 dBi	10.5 dBi
Range (Estimated)	400~1000m	800~3000m	1500~5000m	200~800m
Extension Cable	-	V	-	V
Connector	N-Jack	N-Jack	N-Jack	SMA-RPSMA

Installation over 2-Wire

The POT system, one master & one slave units, provides a long-reach Ethernet extension with remote Power over Ethernet (PoE) capability over a 2-wire line.



PoE Repeater over 2-wire



POT-0100

PoE Extender, Transmitter, Over 2-wire

- 2-wire cables are used to connect 100Mbps Fast Ethernet PoE devices
- Maximum distance up to 400 meters for 24 AWG cable
- Maximum data rate up to 60 Mbps full duplex
- Remote PoE capability for PD devices of WiFi AP, IP camera, IP telephones



POT-0110

PoE Extender, Receiver, Over 2-wire

- 2-wire cables are used to connect 100Mbps Fast Ethernet PoE devices
- Maximum distance up to 400 meters for 24 AWG cable
- Maximum data rate up to 60 Mbps full duplex
- Remote PoE capability for PD devices of WiFi AP, IP camera, IP telephones



POT-1110

- **PoE Extender, Receiver, Over 2-wire, Outdoor** - 2-wire cables are used to connect 100Mbps Fast
- Ethernet PoE devices
- Maximum distance up to 400 meters for 24 AWG cable
- Maximum data rate up to 60 Mbps full duplex
- IP65 Weatherproof



Surveillance Deployment for Transportation

The FCS-3071/FCS-3072/FCS-3093 cameras feature shockproof and weatherproof IP-66/IP-68 housing, specially designed for rolling stock applications such as buses, ambulance services or trains. Combined with a PoE switch, the cameras can be operated and powered from a single Ethernet cable. A Network Video Recorder offers a complete recoding solution which connects directly to a 3G router for real-time monitoring, video recording and playback. TThe cameras also come complete with a Micro SD/SDHC card slot for local recording.




Ethernet Cable (RJ-45) PoE (Power + Data)



Free 64-CH Surveillance Management Software



Central Room Monitoring



Related Products



NVR-1204/NVR-1209/NVR-1216 Network Video Recorder, 4/9/16-Channel - HDMI local display

- Display Up to 4-Megapixel (local display), Up to 10-Megapixel (remote display)
- Recording throughput 30 fps per channel -120fps, 270fps, 480 fps total per model
- Support scheduled recording, event recording, event speed-up recording
- 2-bay Desktop -3.5 inch Serial ATA support up to 8TB total



FEP-0812 4 FE PoE + 4 FE Switch

- Provides 8-Port 10/100Mbps Ethernet Switch with 4 shared PoE ports
- Fully compliant with the IEEE 802.3af PoE
- standard
- Supports over current and circuit shorting
- protection - Total Power Budget: 61.6W

INDEX

30H-1400 30H-1401	Camera PoE Outdoor Enclosure Camera PoE Outdoor Enclosure, IR LE	1 1
OH-1410	Camera PoE Outdoor Enclosure, FEVE Coating	1
OH-1411	Camera PoE Outdoor Enclosure, IR LEDs, FEVE Coating	1
AS-1200	3~8mm Vari-focal Lens	1
AS-1300	2.8~8.5mm Vari-focal Day/Night Megapixel Lens	1
AS-2101	Mount Kit for all Dome Cameras	
AS-2313	Wall Mount for Indoor Domes	1
AS-2314	Wall Mount for Outdoor Domes	
AS-2316	Wall mount for mini dome mini fisheye	1
AS-2504	Pole Mount	1
AS-3000	Outdoor Housing	1
AS-3001	Flush Mount Kit	1
AS-3002	Flush Mount Kit	
AS-3003	Flush Moulit Kit	1
AS-3004	Flush Mount Kit T-Bar Ceiling Mount	
CAS-3100 CAS-3101	I-Bar Ceiling Mount	
AS-3101	Wall Mount Bracket	
AS-3103	Bracket for Indoor Box	
AS-3105		1
AS-3201	Mini Pendant	
AS-3221		1
AS-3221	Description: Corner Plate Mount	
AS-3223	Corner Thin Box Mount	
CAS-3241	Description: Straight Tube, 25cm	
AS-3242	Description: Straight Tube, 50cm	
CAS-3261	Pole Thin Direct Mount	
AS-3263	Pole Thin Box Mount	1
CAS-3281	Wall Box Mount	1
AS-3291	Outdoor Power Box (110-115V AC)	1
AS-3292	Outdoor Power Box (220-230V AC)	1
CAS-4001	Pole Mount Kit for Outdoor Camera Enclosure	
AS-4200	USB Joystick for P/T/Z Network Camera	
CAS-3030	IR Illuminator (30m,80 view angle, IP66 Housing)	
CAS-3300	Ceiling Bracket	
CAS-4312	Wall Mount Bracket, Cable Management	1
) DOH-1000	Domed Outdoor Housing	1
	Domed Outdoor Housing	1
	-	
	Heavy-Duty Domed Outdoor Housing	1
DOH-1100	Heavy-Duty Domed Outdoor Housing	1
OOH-1100	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af	1
CS-0051	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR	1
CS-0051	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel,	1 1
DOH-1100 CS-0032 CS-0051 CS-0071	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night	1 1
OOH-1100 CS-0032 CS-0051 CS-0071 CS-1131	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night	1
CS-0032 CS-0032 CS-0051 CS-0071 CS-1131	Heavy-Duty Domed Outdoor Housing	1 1
00H-1100 CS-0032 CS-0051 CS-0071 CS-01131 CS-1131 CS-1150	Heavy-Duty Domed Outdoor Housing	1 1
CONTINUE CON	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR	1 1 1
200H-1100 : :CS-0032 :CS-0051 :CS-0071 :CS-0071 :CS-1150 :CS-1152 :CS-1160	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 9-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, UDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, UDR Coom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR	1 1 1
200H-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR	1 1
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Com Network Camera, 3-Megapixel, PoE 802.3af, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, URD Fixed Oome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12k, UDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, ILEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af,	1 1 1
CS-0032 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, 2-Megapixel, Day & Night Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Ome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 17x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 17x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 17x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 17x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 18 LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af	1
CS-0132 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3055	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 7-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12 LDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af Fixed Dome Network Camera, 3-Megap	1
CS-0132 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3055	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, UDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, UDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Megapixel, PoE 802.3af,	1
CG-0032 CG-0032 CG-0032 CG-0051 CG-0071 CG-1131 CG-1150 CG-1152 CG-1160 CG-3053 CG-3053 CG-3053 CG-3055 CG-3063	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Pixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Tom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, POE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, POE 802.3af, Day & Night, ILEDS, WDR Fixed Dome Network Camera, 5-Megapixel, POE 802.3af, Fixed	1 1 1
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3063 CS-3064	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, UDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IX, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR	1
CS-3054 CS-3055 CS-3055 CS-1150 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3055 CS-3064	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, T2x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs	1
CS-0032 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3064 CS-3065	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11 LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, Po	
xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 17x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11 R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11 R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11 R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11 R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night,	
xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, UDR Sixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, UDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IX, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, MDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR Fixed Dome Network Camera, 5-Megapixel, PoE	1 1 1 1 1
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3064 CS-3065 CS-3071	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, <	1 1 1 1 1 1
xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, T2x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, ILEDs, WDR </td <td> 1 1 1 1 1 1</td>	1 1 1 1 1 1
xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af,	1 1 1 1 1
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3055 CS-3064 CS-3065 CS-3071 CS-3072 CS-3081 CS-3082	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR Fixed Dome Network Camera, 5-Megapi	1 1 1 1 1 1 1
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3055 CS-3064 CS-3065 CS-3071 CS-3072 CS-3081 CS-3082	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 112, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, LEDs Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, RLEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, MDR	1 1 1 1 1 1 1
DOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-3053 CS-3054 CS-3063 CS-3063 CS-3064 CS-3071 CS-3065 CS-3064 CS-3071 CS-3072 CS-3081 CS-3082 CS-3083	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, Tax, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, MDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, WDR, Vandalproof, Vibrationproof	
DOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1152 CS-3053 CS-3054 CS-3065 CS-3065 CS-3065 CS-3071 CS-3072 CS-3082 CS-3083 CS-3083 CS-3081 CS-3083 CS-3081 CS-3083	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, Fixed Network Camera, 5-Megapixel, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Com Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, R LDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 11, LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Poe 802.3af, WDR, Vandalproof, Vibratinoproof Fixed Dom	
DOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-3053 CS-3054 CS-3063 CS-3063 CS-3064 CS-3071 CS-3065 CS-3064 CS-3071 CS-3072 CS-3081 CS-3082 CS-3083	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, T2x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 18 LEDs Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, WDN, Vandalproof, Vibrationproof Fixed Dome Network Camera, 7-Megapixel, Outdoor, PoE 802.3af, Day & Night Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR <td></td>	
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1152 CS-3053 CS-3054 CS-3063 CS-3064 CS-3065 CS-3064 CS-3071 CS-3081 CS-3082 CS-3091 CS-3092	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, T2x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 18 LEDs Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, WDN, Vandalproof, Vibrationproof Fixed Dome Network Camera, 7-Megapixel, Outdoor, PoE 802.3af, Day & Night Fixed Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR <td></td>	
DOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1152 CS-3053 CS-3054 CS-3065 CS-3065 CS-3065 CS-3071 CS-3072 CS-3082 CS-3083 CS-3083 CS-3081 CS-3083 CS-3081 CS-3083 CS-3081	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 3-Megapixel, PoE 802.3af, 2-Megapixel, Day & Night Fixed Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 112 LDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDS, WDR	
DOH-1100 CS-0032 CS-0031 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-3053 CS-3054 CS-3063 CS-3064 CS-3065 CS-3064 CS-3065 CS-3081 CS-3082 CS-3083 CS-3081 CS-3082 CS-3081 CS-3083 CS-3081	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af, WDR Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night, T. Zoom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, T.X, WDR Tom Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, TX, WDR Zoom Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, TX, WDR Town Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, TX, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, TX, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera, 7-Megapixel, Outdoor, PoE 802.3af, WDR, Vandalproof, Vibrationproof Fixed Dome Network Camera, 7-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDS, WDR Fixed Dome Network Camera,	
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1131 CS-1150 CS-1152 CS-1160 CS-3053 CS-3054 CS-3063 CS-3064 CS-3065 CS-3064 CS-3071 CS-3083 CS-3081 CS-3092 CS-3093 CS-3094	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af Fixed Network Camera, 5-Megapixel, PoE 802.3af, 2-Megapixel, Day & Night Panoramic Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night Zoom Network Camera, PoE 802.3af, 2-Megapixel, Day & Night, 12x, WDR Fixed Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 12x, WDR Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, 11, R LEDs. Fixed Dome Network Camera, 3-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, PoE 802.3af, Day & Night, IR LEDs, WDR Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, WDR, Vandalproof, Vibrationproof Fixed Dome Network Camera, 5-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs, WDR Fixe	
XOH-1100 CS-0032 CS-0051 CS-0071 CS-1130 CS-1150 CS-1152 CS-1152 CS-1160 CS-3053 CS-3054 CS-3063 CS-3064 CS-3065 CS-3071 CS-3072 CS-3081 CS-3082 CS-3091 CS-3092 CS-3093	Heavy-Duty Domed Outdoor Housing Fixed Network Camera, 3-Megapixel, PoE 802.3af,	

	PTZ Dome Network Camera, PoE+ 802.3af/at, 2-Megapixel,	
FCS-4042		13
FCS-4043	PTZ Dome Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, 10x, WDR	13
FCS-4044	PTZ Dome Network Camera, 5-Megapixel, PoE 802.3af, Outdoor, Day & Night, 10x, WDR	13
FCS-4101	PT Dome Network Camera, IR LEDs, PoE 802.3af, 2-Megapixel, Day & Night	13
FCS-5042	Zoom Network camera, PoE 802.3af, IR LEDs, 2-Megapixel, Day & Night, Outdoor, 10x	8
FCS-5051	Fixed Network Camera, IR LEDs, PoE 802.3af, IR LEDs,	5
FCS-5053	Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af, Day & Night, IR LEDs	6
FCS-5054	Fixed Network Camera, 3-Megapixel, PoE 802.3af, Outdoor, Day & Night, IR LEDs, WDR 10/100Mbps	6
FCS-5055	Zoom Network Camera, 3-Megapixel, Outdoor, PoE 802.3af,	8
FCS-5056	Day & Night, IR LEDs, 12x, WDR Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af,	8
FCS-5057	Day & Night, IR LEDs, WDR Fixed Network Camera, 3-Megapixel, Outdoor, PoE 802.3af,	-
FCS-5061	Day & Night, IR LEDs, WDR 10/100Mbps Fixed Network Camera, IR LEDs, PoE+ 802.3af/at, 5-Megapixel	
FCS-5063	Day & Night, Outdoor Fixed Network Camera, 5-Megapixel, Outdoor, PoE 802.3af,	7
FCS-5064	Day & Night, IR LEDs, WDR Fixed Network Camera, 5-Megapixel, Outdoor, PoE 802.3af,	7
FCS-5065	Day & Night, IR LEDs, WDR Zoom Network Camera, 5-Megapixel, Outdoor, PoE 802.3af,	7
FCS-6020	Day & Night, IR LEDs, 12x, WDR PT Network Camera, Day & Night, PoE 802.3af, IR LEDs,	8
FCS-7001	2-Megapixel	16 26
FCS-7001 FCS-7004		26 26
FCS-8005	4-CH Analog Camera Capture Card	
FCS-8006	16-CH Analog Camera Capture Card	26
FCS-9364	OneSecure Video Management Software	
FEP-0811	8-Port Fast Ethernet PoE Switch, 123.2W, PoE Plus	27
FEP-0812	Unmanaged Fast Ethernet Switch, 4 Ports RJ45, 4 Ports RJ45 PoE Plus, 61.6W	27
FEP-1611	Unmanaged Switch, 16 Ports Fast Ethernet PoE+, 240W	27
FEP-1612	Unmanaged Switch, 16 Ports Fast Ethernet PoE+, 480W	27
FGP-2410		27
FGP-2412	24 FE PoE-Plus + 2 GE Combo SFP Switch, 480W	27
50111 0500		27
FSW-0503		27
FSW-0513	4 FE High Power PoE + 1 FE Switch, 120W	27
FSW-0513	4 FE High Power PoE + 1 FE Switch, 120W	
FSW-0513 FSW-1671 G	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 1 Port RJ45, 61.6W,	27 27
FSW-0503 FSW-0513 FSW-1671 GEP-0520 GEP-0521	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W	27
FSW-0513 FSW-1671 G GEP-0520 GEP-0521	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0950	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0950 GEP-1621	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 12 Port RJ45, 61.6W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Plus, 1 Port RJ45 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W	27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0520 GEP-0820 GEP-0822 GEP-0822 GEP-0950 GEP-1621 GEP-1622 GEP-1622 GEP-2450	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0950 GEP-1621 GEP-1622 GEP-2450 GEP-2450	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0821 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2672	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0821 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2672	4 FE High Power PoE + 1 FE Switch, 120W	27 27 27 27 27 27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-1621 GEP-1622 GEP-1622 GEP-2671 GEP-2671 GEP-2672 GEP-2670	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE SePort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Bort Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 440W 24 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 24 GE PoE-Plus with 4 Shared SFP Web Smart Switch, 185W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 370W	27 27 27 27 27 27 27 27 27 27 27 27 27 27 27 27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-1621 GEP-1621 GEP-1621 GEP-2671 GEP-2672 GEP-2670 I FE-0500 IFE-0501	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RI45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RI45 PoE Plus, 1 Port RI45 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 24 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 4FE PoE + 1 FE Industrial Switch 4FE PoE + 1 FE MMF SC Industrial Switch, 2km	27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-1621 GEP-1621 GEP-1621 GEP-2671 GEP-2672 GEP-2670 I FE-0500 IFE-0501	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE SePort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Bort Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 440W 24 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 24 GE PoE-Plus with 4 Shared SFP Web Smart Switch, 185W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 370W	27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-1621 GEP-1621 GEP-1621 GEP-2671 GEP-2672 GEP-2670 I IFE-0500 IFE-0500 IFE-0502 N	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 12 Port RJ45, 61.6W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE BePort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Bort Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 440W 20 GE PoE-Plus + 1 GE SFP Web Smart Switch, 18SW 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 4 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 4 FE PoE + 1 FE Industrial Switch 4 FE PoE + 1 FE Industrial Switch, 2xm 4 FE PoE + 1 FE SMF SC Industrial Switch, 30km	27 27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0521 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-0822 GEP-1622 GEP-1622 GEP-1622 GEP-2671 GEP-2671 GEP-2670 I IFE-0500 IFE-0500 IFE-0500 IFE-0502 N NVR-1204	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120.4W 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE PoE-Plus with 4 Shared SFP Web Smart Switch, 18SW 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 20 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 4 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 4 FE PoE + 1 FE Industrial Switch 4 FE PoE + 1 FE MMF SC Industrial Switch, 20km 4 FE PoE + 1 FE SMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel	27
FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-1621 GEP-1622 GEP-2671 GEP-2670 GEP-2670 GEP-2670 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0501 IFE-0502 NWR-1204 NVR-1204	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 9 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 4 FE PoE + 1 FE Industrial Switch 4 FE PoE + 1 FE MMF SC Industrial Switch, 2km 4 FE PoE + 1 FE SMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel	27
FSW-0513 FSW-0513 GEP-0520 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0821 GEP-1621 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2671 GEP-2670 IFE-0500 IFE-0500 IFE-0501 IFE-0501 IFE-0501 IFE-0502 NWR-1204 NVR-1204 NVR-1204	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 24 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 47 FE PoE + 1 FE Industrial Switch 47 FE PoE + 1 FE MMF SC Industrial Switch, 2km 47 FE PoE + 1 FE SMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel	27 24 24
FSW-0513 FSW-0513 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0820 GEP-0822 GEP-0820 GEP-1621 GEP-0500 GEP-1621 GEP-2671 GEP-2672 GEP-2670 GEP-2670 FFE-0500 IFE-0500 IFE-0500 IFE-0501 IFE-0501 IFE-0502 NWR-1204 NVR-1204 NVR-1204 NVR-1216	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 123.2W Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 24 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 47 FE PoE + 1 FE Industrial Switch 47 FE PoE + 1 FE MMF SC Industrial Switch, 2km 47 FE PoE + 1 FE SMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel	27 24 24 24 24
FSW-0513 FSW-0513 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0820 GEP-0820 GEP-0820 GEP-0520 GEP-0520 GEP-1621 GEP-1622 GEP-1621 GEP-1622 GEP-2672 GEP	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 24 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 47 FE PoE + 1 FE Industrial Switch 47 FE PoE + 1 FE Industrial Switch 47 FE PoE + 1 FE MMF SC Industrial Switch, 2km 47 FE PoE + 1 FE MMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 4-Channel	27 24 24 24 24 33
FSW-0513 FSW-0513 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0820 GEP-1621 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2671 GEP-2670 I IFE-0500 IFE-0501 IFE-0502	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 4 Ports RJ45 PoE 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Plus, 1 Port RJ45 8 FPort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE POE-Plus + 1 GE SPP Web Smart Switch, 130W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 2 GE SFP L2 Managed Switch, 375W 4 FE POE + 1 FE Industrial Switch 4 FE POE + 1 FE MMF SC Industrial Switch, 20km 4 FE POE + 1 FE SMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 4-Channel Network Video Recorder, 4-Channel 9dBi 2.4GHz Omni-directional Indoor/Outdoor Antenna Kit -	27 24 24 24 33 33 33
FSW-0513 FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-1621 GEP-1621 GEP-1621 GEP-2671 GEP-2671 GEP-2670 IFE-0500 IFE-0501 IFE-0501 IFE-0501 IFE-0501 IFE-0501 IFE-0501 P NVR-1204 NVR-1204 NVR-1204 NVR-1209 OAN-2090 OAN-2151 PFE-1001R	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Horts RJ45 PoE 9 Hort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 4 GE PoE + 1 FE Industrial Switch 4 FE PoE + 1 FE Industrial Switch, 240M 4 FE PoE + 1 FE SMF SC Industrial Switch, 30km 9 Het vork Video Rec	27 24 24
FSW-0513 FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0822 GEP-0822 GEP-0950 GEP-1621 GEP-2672 GEP-2671 GEP-2672 GEP-2670 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 OAN-2109 OAN-2090 OAN-2090 OAN-2151 PFE-1001T	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Plus, 1 Port RJ45 9 Arotts RJ45 PoE Plus, 1 Port RJ45 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 9 -Bort Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE POE-Plus + 1 GE SPP Web Smart Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 2 GE SFP L2 Managed Switch, 375W 4 FE POE + 1 FE Industrial Switch 4 FE POE + 1 FE Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Netw	27 24 24 33 33 28
FSW-0513 FSW-0513 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0820 GEP-0820 GEP-0820 GEP-0520 GEP-0520 GEP-1621 GEP-1622 GEP-1621 GEP-1622 GEP-2672 GEP	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 9 Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 16-Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 8 GE PoE-Plus + 1 GE SFP Web Smart Switch, 130W 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 18SW 20 GE PoE-Plus + 4 GE PoE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 48 GE PoE-Plus + 2 GE SFP L2 Managed Switch, 37SW 47 FE PoE + 1 FE Industrial Switch 47 FE PoE + 1 FE Industrial Switch, 30km 47 FE PoE + 1 FE MMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 16-Channel Network Video Recorder, 16-Channel 9dBi 2.4GHz Omni-directional Indoor/Outdoor	27 24 33 33 28
FSW-0513 FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0820 GEP-0821 GEP-0820 GEP-0821 GEP-0820 GEP-2671 GEP-1021 GEP-2672 GEP-2672 GEP-2672 GEP-2670 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0501 FF-0500 PPE-1001R PFE-1001R PFE-1001R PFE-1001R PFE-1001R	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 4 Ports RJ45 PoE 9 Port Gigabit Ethernet Switch, 20W, 4 Ports RJ45 PoE 9 Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE POE-Plus + 1 GE SPP Web Smart Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 2 GE SFP L2 Managed Switch, 375W 4 FE POE + 1 FE Industrial Switch 4 FE POE + 1 FE Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel <td> 27 24 24 33 33 28 28 </td>	27 24 24 33 33 28
FSW-0513 FSW-0513 FSW-1671 GEP-0520 GEP-0520 GEP-0521 GEP-0820 GEP-0821 GEP-0822 GEP-0821 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2671 GEP-2671 GEP-2672 GEP-2670 IFE-0500 IFE-0500 IFE-0500 IFE-0500 IFE-0500 PFE-1001R PFE-1001R PFE-1001R PFE-1011R PFE-1011R	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 4 Ports RJ45 PoE 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE Plus, 1 Port RJ45 8 FPort Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 440W 20 GE POE-Plus + 1 GE SPP Web Smart Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 2 GE SFP L2 Managed Switch, 375W 4 FE POE + 1 FE Industrial Switch 4 FE POE + 1 FE MMF SC Industrial Switch, 20km 4 FE POE + 1 FE MMF SC Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 4-Channel Network Video Recorder, 4-Channel 9dBi 2.4GHz Omni-directional Outdoor Antenna	27 28 28
FSW-0513 FSW-0513 FSW-1671 GEP-0520 GEP-0521 GEP-0521 GEP-0821 GEP-0822 GEP-0521 GEP-1622 GEP-1621 GEP-1622 GEP-2671 GEP-2671 GEP-2671 GEP-2672 GEP-2670 IFE-0500 IFE-0500 IFE-0500 IFE-0501 FFE-0501 FFE-0501 FFE-0502 NWR-1209 OAN-2090 OAN-2090 OAN-2151 P PFE-1001R PFE-1001R	4 FE High Power PoE + 1 FE Switch, 120W 8 FE PoE + 8 FE Web Smart Switch, 123.2W 9 Unmanaged Gigabit Ethernet Switch, 120W, 4 Ports RJ45 PoE 4 Ports RJ45 PoE 9 Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 61.6W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 123.2W 8 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 9 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 16 -Port Gigabit Ethernet PoE Switch, PoE Plus, 240W 20 GE POE-Plus + 1 GE SPP Web Smart Switch, 185W 20 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 4 GE POE-Plus Combo SFP + 2 GE SFP L2 Managed Switch, 370W 48 GE POE-Plus + 2 GE SFP L2 Managed Switch, 375W 4 FE POE + 1 FE Industrial Switch 4 FE POE + 1 FE Industrial Switch, 30km Network Video Recorder, 4-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Network Video Recorder, 9-Channel Net	27 24 24 24 28

POI-2001	PoE Injector, Gigabit Ethernet	31
POI-2002	PoE Injector	31
POI-3000	PoE+ Injector, Gigabit Ethernet	31
POI-3002	PoE Injector, 30W	31
POI-4000	PoE Injector, 60W	31
POR-0100	PoE Repeater, Cascadable	29
POR-0102	PoE Repeater, 2 Ports, Cascadable	29
POR-0120	PoE Repeater, Gigabit Ethernet, Cascadable	29
POR-0122	PoE Repeater, Gigabit Ethernet, 2 Ports, Cascadable	29
POR-0200	PoE+ Repeater, Cascadable	30
POR-0202	PoE+ Repeater, 2 Ports, Cascadable	30
POR-0220	PoE+ Repeater, Gigabit Ethernet, Cascadable	30
POR-0222	PoE+ Repeater, Gigabit Ethernet, 2 Ports, Cascadable	30
POR-1100	PoE Repeater, Outdoor, Cascadable	29
POR-1102	PoE Repeater, 2 Ports, Outdoor, Cascadable	29
POR-1200	PoE+ Repeater, Outdoor, Cascadable	30
POR-1202	PoE+ Repeater, 2 Ports, Outdoor, Cascadable	
POR-1220	PoE+ Repeater, Gigabit Ethernet, Outdoor, Cascadable	30
POR-1222	PoE+ Repeater, 2 Ports, Gigabit Ethernet, Outdoor, Cascadable	30
POS-1002	5-12V DC PoE Splitter	31
POS-3000	5-12V DC Gigabit PoE-Plus Splitter	31
POS-4000	12V DC High Power PoE Splitter	31
POS-4001	12VDC High Power PoE Splitter	31
POS-4002	24V AC High Power PoE Splitter	
POT-0100	PoE Extender, Transmitter, Over 2-wire	34
POT-0110	PoE Extender, Receiver, Over 2-wire	34
POT-1110	PoE Extender, Receiver, Over 2-wire, Outdoor	34
W		
WAB-5120	5GHz Wireless Access Point, Built-in Antenna, 300Mbps 802.11a/n, Passive PoE, Outdoor	33
WAB-6120	Wireless Access Point, Built-in Antenna, 150Mbps 802.11b/g/n, Passive PoE, Outdoor	33
WAN-2181	18dBi 2.4GHz Directional Panel Antenna	33
WAN-7100	10.5dBi 2.4GHz Directional Dual-Polarization Patch Antenna Kit	33
WAP-6101	Managed Ceiling Wireless Access Point, 300Mbps 802.11b/g/n, Gigabit Ethernet, 802.3af PoE, Built-in Antenna	n 3:
WAP-6103	Managed Ceiling Wireless Access Point, 802.3af PoE, 300Mbp 802.11b/g/n, Fast Ethernet, Built-in Antenna	
WCS-6020	PT Network Camera, IR LEDs, 150Mbps 802.11b/g/n, 2-Megapixel, Day & Night	10
WCS-6050	PT Network Camera, IR LEDs, 150Mbps 802.11b/g/n, 5-Megapixel, Day & Night	10

level $o \cap e$

Digital Data Communications Group www.level1.com

Global Headquarters: Digital Data Communications GmbH, Germany

Global Offices: Germany, Taiwan, Australia, Belgium, Brasil, Colombia, Denmark, Greece, Italy, Kenya, the Netherlands, Portugal, Slovenia, Spain, U.A.E

Distributed By:

Technical specifications are subject to change without notice. No responsibility is taken for errors in contents or printing. All mentioned brand names and trademarks are property of their respective owners.
© Copyright Digital Data Communications GmbH. All Rights Reserved. Zeche-Norm Str. 25, 44319 Dortmund, Germany